

# Attachment I

## **4.2 Day-Ahead Markets and Schedules**

### **4.2.1 Day-Ahead Load Forecasts, Bids and Bilateral Schedules**

#### **4.2.1.1 General Customer Forecasting and Bidding Requirements**

Subject to the two earlier submission deadlines set forth below, by 5 a.m. on the day prior to the Dispatch Day: (i) All LSEs serving Load in the NYCA shall provide the ISO with Load forecasts for the Dispatch Day and the day after the Dispatch Day; and (ii) Customers and Transmission Customers submitting Bids in the Day-Ahead Market shall provide the ISO, consistent with ISO Procedures:

- a. Bids to supply Energy, including Bids to supply Energy in Virtual Transactions;
- b. Bids to supply Ancillary Services;
- c. Requests for Bilateral Transaction schedules;
- d. Bids to purchase Energy, including Bids to purchase Energy in Virtual Transactions and Bids to withdraw Energy by Withdrawal-Eligible Generators;
- e. Demand Reduction Bids; and
- f. For Behind-the-Meter Net Generation Resources, the forecasted Host Load for each hour of the Dispatch Day.

By 4:50 a.m. on the day prior to the Dispatch Day, all Customers or Transmission Customers shall submit Bids for External Transactions at the Proxy Generator Bus associated with the Cross-Sound Scheduled Line, the Neptune Scheduled Line, the Linden VFT Scheduled Line, or the HTP Scheduled Line.

By 4:45 a.m. on the day prior to the Dispatch Day, all Customers or Transmission Customers shall submit Bids that include revised fuel type or fuel price information to the ISO's Market Information System.

In general, the information provided to the ISO shall include the following:

#### **4.2.1.2 Load Forecasts**

The Load forecast shall indicate the predicted level of Load in MW by Point of Withdrawal for each hour.

#### **4.2.1.3 Bids by Suppliers Using the ISO-Committed Flexible, Self-Committed Flexible or ISO-Committed Fixed Bid Modes to Supply Energy and/or Ancillary Services**

##### **4.2.1.3.1 General Rules**

Day-Ahead Bids by Suppliers using the ISO-Committed Flexible, Self-Committed Flexible or ISO-Committed Fixed bid modes shall identify the Capacity, in MW, available for commitment in the Day-Ahead Market (for every hour of the Dispatch Day) and the price(s) at which the Supplier will voluntarily enter into dispatch commitments. If the Supplier elects to participate in the Day-Ahead Market, and is within a defined electrical boundary, electrically interconnected with, and routinely serves a Host Load (which Host Load does not consist solely of Station Power) at a single PTID, it can only participate in the Day-Ahead Market as a Behind-the-Meter Net Generation Resource. If the Supplier is a Behind-the-Meter Net Generation Resource, the ISO shall only consider price-MW pairs in excess of the forecasted Host Load for the Resource.

A Supplier's Day-Ahead Bids for an Energy Storage Resource to withdraw Energy and to inject Energy shall be submitted as a single, continuous, bid curve representing the Capacity, in MW, available for commitment in the Day-Ahead Market for each hour of the Dispatch Day, and shall indicate whether the Resource's Energy Level will be ISO- or Self-Managed. An Energy Storage Resource may not change its Energy Level Management election within the Day-Ahead Market evaluation period (*i.e.*, within a single day).

If the Supplier using the ISO-Committed Flexible or Self-Committed Flexible bid mode is eligible to provide Regulation Service or Operating Reserves under Rate Schedules 3 and 4 respectively of this ISO Services Tariff, the Supplier's Bid may specify the quantity of Regulation Capacity it is making available and shall specify an emergency response rate that determines the quantity of Operating Reserves that it is capable of providing. Offers to provide Regulation Service and Operating Reserves must comply with the rules set forth in Rate Schedules 3 and 4 of this ISO Services Tariff. If a Supplier that is eligible to provide Operating Reserves does not submit a Day-Ahead Availability Bid for Operating Reserves, its Day-Ahead Bid shall be rejected in its entirety. A Behind-the-Meter Net Generation Resource that is comprised of more than one generating unit that is dispatched as a single aggregate unit at a single PTID is not qualified to provide Regulation Service or Spinning Reserves. A Supplier may resubmit a complete Day-Ahead Bid, provided that the new Bid is timely. See Section 4.2.1.9 for bidding requirements for Demand Side Resources offering Energy in the Day-Ahead Market.

Suppliers other than Demand Side Resources entering a Bid into the Day-Ahead Market may also enter Day-Ahead Bids for each of the next nine (9) Dispatch Days. If not subsequently modified or withdrawn, these offers for subsequent Dispatch Days may be used by the ISO as offers from these Suppliers in the Day-Ahead Market for these subsequent Dispatch Days. For Suppliers that are providing Unforced Capacity in the ISO-administered ICAP Market for the month in which the Dispatch Day and the nine-day advance bidding period are encompassed, the ISO may enter the eighth day offer as the Bid for that Supplier's ninth day, if there is, otherwise no ninth-day Bid.

#### **4.2.1.3.2 Bid Parameters**

Day-Ahead Bids by Suppliers using the ISO-Committed Flexible, Self-Committed Flexible or ISO-Committed Fixed bid modes may identify-variable Energy price Bids, consisting of up to eleven monotonically increasing, constant cost incremental Energy steps, and other parameters described in ISO Procedures. Day-Ahead Bids from Demand Side Resources offering Operating Reserves or Regulation Service shall be ISO-Committed Flexible and shall have an Energy Bid price no lower than the Monthly Net Benefit Offer Floor. Day-Ahead offers by Intermittent Power Resources that depend on wind as their fuel shall be ISO-Committed Flexible and shall include a Minimum Generation Bid of zero megawatts and zero costs and a Start-Up Bid of zero cost.

Day-Ahead Bids by ISO-Committed Fixed and ISO-Committed Flexible Generators, other than bids from Intermittent Power Resources that depend on wind as their fuel, shall also include Minimum Generation Bids and hourly Start-Up Bids. Bids shall specify whether a Supplier is offering to be ISO-Committed Fixed, ISO-Committed Flexible, Self-Committed Fixed, or Self-Committed Flexible.

#### **4.2.1.3.3 Upper Operating Limits, Lower Operating Limits, and Response Rates**

All Bids to supply Energy and Ancillary Services must specify a  $UOL_N$  and a  $UOL_E$  for each hour. A Resource's  $UOL_E$  may not be lower than its  $UOL_N$ . Bids from Withdrawal-Eligible Generators shall also specify the Generator's Lower Operating Limit for each hour.

Bids from Suppliers for Generators supplying Energy and Ancillary Services must specify a normal response rate and may provide up to three normal response rates provided the minimum normal response rate may be no less than one percent (1%) of the Generator's Operating Capacity per minute. All Bids from Suppliers for Generators supplying Energy and

Ancillary Services must also specify an emergency response rate which shall be equal to or greater than the maximum normal response rate of the Generator.

Bids from Suppliers offering Operating Reserves or Regulation Service from Demand Side Resources must specify a normal response rate and an emergency response rate provided that the emergency response rate may not be lower than the normal response rate. For Demand Side Resources the minimum acceptable response rate is one percent (1%) of the quantity of Demand Reduction the Demand Side Resource produces per minute.

#### **4.2.1.3.4 Additional Parameters for Energy Storage Resources**

In addition to the parameters that Suppliers submit for Energy Storage Resources because they are Generators, specific parameters may apply to some Bids for Energy Storage Resources. Consistent with the ISO Procedures, Bids from Suppliers for Energy Storage Resources supplying Energy and Ancillary Services may be required to specify ~~whether the Energy Level will be ISO-Managed or Self-Managed,~~ the Beginning Energy Level, ~~and~~ the Energy Storage Resource's Roundtrip Efficiency, ~~and.~~ ~~An Energy Storage Resource~~ must ~~also~~ specify its Upper and Lower Storage Limits. The Energy Level for an Energy Storage Resource shall be managed by the Supplier unless the Supplier elects, in its Bids, to be ISO-Managed.

The Day-Ahead Schedule for Energy Storage Resources with ISO-Managed Energy Levels will reflect the Resource's Energy Level constraints, including the Beginning Energy Level, the Upper and Lower Storage Limits, and the Resource's Roundtrip Efficiency. An Energy Storage Resource that self-manages its Energy Level is obligated to submit Bids that are consistent with its Energy Level constraints, and the Day-Ahead optimization will not honor the above-identified Energy Level constraints.

#### **4.2.1.4 Offers to Supply Energy from Self-Committed Fixed Generators**

Self-Committed Fixed Generators shall provide the ISO with a schedule of their expected Energy output and withdrawals (when applicable) for each hour. Self-Committed Fixed Generators are responsible for ensuring that any hourly changes in output are consistent with their response rates. Self-Committed Fixed Generators shall also submit UOL<sub>NS</sub>, UOL<sub>ES</sub> and variable Energy Bids for possible use by the ISO in the event that RTD-CAM initiates a maximum generation pickup, as described in Section 4.4.3 of this ISO Services Tariff.

#### **4.2.1.5 Bids to Supply Energy in Virtual Transactions**

Customers submitting Bids to supply Energy in Virtual Transactions shall identify the Energy, in MW, available in the Day-Ahead Market (for every hour of the Dispatch Day) and the price(s) at which the Customer will voluntarily make it available.

#### **4.2.1.6 Bids to Purchase Energy in Virtual Transactions**

Customers submitting bids to purchase Energy in Virtual Transactions shall identify the Energy, in MW, to be purchased in the Day-Ahead Market (for every hour of the Dispatch Day) and the price(s) at which the Customer will voluntarily purchase it.

#### **4.2.1.7 Bilateral Transactions**

Transmission Customers requesting Bilateral Transaction schedules shall identify hourly Transaction quantities (in MW) by Point of Injection and Point of Withdrawal, minimum run times associated with Firm Point-to-Point Transmission Service, if any, and shall provide other information (as described in ISO Procedures).

#### **4.2.1.8 Bids to Purchase LBMP Energy in the Day-Ahead Market**

Each purchaser shall submit Bids indicating the hourly quantity of Energy, in MW, that it will purchase from the Day-Ahead Market for each hour of the following Dispatch Day. These Bids shall indicate the quantities to be purchased by Point of Withdrawal. The Bids may identify prices at which the purchaser will voluntarily enter into the Transaction.

#### **4.2.1.9 Day-Ahead Bids from Demand Reduction Providers and DSASP Providers to Supply Energy from Demand Reductions**

Demand Reduction Providers and DSASP Providers offering Energy from Demand Side Resources shall submit Bids: (i) identifying the amount of Demand Reduction, in MWs in accordance with Section 4.1.4, that is available for commitment in the Day-Ahead Market (for every hour of the dispatch day) and (ii) identifying the prices at which the Demand Reduction Provider or DSASP Provider will voluntarily enter into dispatch commitments to reduce demand; provided, however, the price at which the Demand Reduction Provider or DSASP Provider will voluntarily enter into dispatch commitments to reduce demand shall be no lower than the Monthly Net Benefit Offer Floor, as determined in accordance with this section. The Bids will identify the minimum period of time that the Demand Reduction Provider or DSASP Provider is willing to reduce demand, however the minimum period may not be less than one hour. The Bid may separately identify the Demand Reduction Provider's Curtailment Initiation Cost. Demand Reduction Bids from Demand Reduction Providers that are not accepted in the Day-Ahead Market shall expire at the close of the Day-Ahead Market.

The ISO shall perform the Net Benefits Test and post on its web site the Monthly Net Benefit Offer Floor for each month by the 15<sup>th</sup> of the preceding month in accordance with ISO Procedures. The Net Benefits Test shall establish the threshold price below which the dispatch of Energy from Demand Side Resources is not cost-effective. The Net Benefits Test shall

consist of the following steps: (1) the ISO shall compile hourly supply curves for the Reference Month; (2) the ISO shall develop the average supply curve for the Study Month by updating the Reference Month supply curves for retirements and new entrants, and adjusting offers for changes in fuel prices; (3) the ISO shall apply an appropriate mathematical formula to smooth the average supply curve; and (4) the ISO shall evaluate the smoothed average supply curve to determine the Monthly Net Benefit Floor for the Study Month. The ISO shall apply the Monthly Net Benefit Offer Floor, as so calculated, to Bids submitted by Demand Response Providers for all hours in the Study Month.

The ISO shall promptly post corrections, where necessary, to the Monthly Net Benefit Offer Floor. Corrections shall only apply to errors in conducting the calculations described above and/or in posting the properly calculated Monthly Net Benefit Offer Floor. Corrections shall not include recalculations based on changes in gas prices as set forth above. The ISO shall not use any correction to the Monthly Net Benefit Offer Floor to determine revised Day-Ahead Market clearing prices for periods prior to the imposition of the correction.

#### **4.2.2 ISO Responsibility to Establish a Statewide Load Forecast**

By 8 a.m., or as soon thereafter as is reasonably possible, the ISO will develop and publish its statewide Load forecast on the OASIS. The ISO will use this forecast to perform the SCUC for the Dispatch Day.

#### **4.2.3 Security Constrained Unit Commitment (“SCUC”)**

Subject to ISO Procedures and Good Utility Practice, the ISO will develop a SCUC schedule over the Dispatch Day using a computer algorithm which simultaneously minimizes the total Bid Production Cost of: (i) supplying power or Demand Reductions to satisfy accepted purchasers’ Bids to buy Energy from the Day-Ahead Market; (ii) providing sufficient Ancillary

Services to support Energy purchased from the Day-Ahead Market consistent with the Regulation Service Demand curve and Operating Reserve Demand Curves set forth in Rate Schedules 3 and 4 respectively of this ISO Services Tariff; (iii) committing sufficient Capacity to meet the ISO's Load forecast and provide associated Ancillary Services; and (iv) meeting Bilateral Transaction schedules submitted Day-Ahead excluding schedules of Bilateral Transactions with Trading Hubs as their POWs. The computer algorithm shall consider whether accepting Demand Reduction Bids will reduce the total Bid Production Cost.

The ISO shall compute all NYCA Interface Transfer Capabilities prior to scheduling Transmission Service Day-Ahead. The ISO shall run the SCUC utilizing the computed Transfer Capabilities, submitted Firm Point-to-Point Transmission Service requests, Load forecasts, and submitted Incremental Energy Bids, Decremental Bids and Sink Price Cap Bids.

The schedule will include commitment of sufficient Generators and/or Demand Side Resources to provide for the safe and reliable operation of the NYS Power System. SCUC will treat a Behind-the-Meter Net Generation Resources and Energy Storage Resources as already being committed and available to be scheduled. Pursuant to ISO Procedures, the ISO may schedule any Resource to run above its  $UOL_N$  up to the level of its  $UOL_E$ . In cases in which the sum of all Bilateral Schedules, excluding Bilateral Schedules for Transactions with Trading Hubs as their POWs, and all Day-Ahead Market purchases to serve Load within the NYCA in the Day-Ahead schedule is less than the ISO's Day-Ahead forecast of Load, the ISO will commit Resources in addition to the Operating Reserves it normally maintains to enable it to respond to contingencies. The purpose of these additional resources is to ensure that sufficient Capacity is available to the ISO in real-time to enable it to meet its Load forecast (including associated Ancillary Services). In considering which additional Resources to schedule to meet the ISO's

Load forecast, the ISO will evaluate unscheduled Imports, and will not schedule those Transactions if its evaluation determines the cost of those Transactions would effectively exceed a Bid Price cap in the hours in which the Energy provided by those Transactions is required. In addition to all Reliability Rules, the ISO shall consider the following information when developing the SCUC schedule: (i) Load forecasts; (ii) Ancillary Service requirements as determined by the ISO given the Regulation Service Demand Curve and Operating Reserve Demand Curves referenced above; (iii) Bilateral Transaction schedules excluding Bilateral Schedules for Transactions with Trading Hubs as their POWs; (iv) price Bids and operating Constraints submitted for Generators or for Demand Side Resources; (v) price Bids for Ancillary Services; (vi) Decremental Bids and Sink Price Cap Bids for External Transactions; and (vii) Bids to purchase or sell Energy from or to the Day-Ahead Market. External Transactions with minimum run times greater than one hour will only be scheduled at the requested Bid for the full minimum run time. External Transactions with identical Bids and minimum run times greater than one hour will not be prorated. The SCUC schedule shall list the hourly injections and withdrawals for: (a) each Customer whose Bid the ISO accepts for the Dispatch Day; and (b) each Bilateral Transaction scheduled Day-Ahead excluding Bilateral Transactions with Trading Hubs as their POWs.

In the development of its SCUC schedule, the ISO may commit and de-commit Generators and Demand Side Resources, based upon any flexible Bids, including Minimum Generation Bids, Start-Up Bids, Curtailment Initiation Cost Bids, Energy, and Incremental Energy Bids and Decremental Bids received by the ISO provided however that: (a) the ISO shall commit zero megawatts of Energy for Demand Side Resources committed to provide Operating Reserves and Regulation Service; and (b) for Behind-the-Meter Net Generation Resources, the

ISO will consider for dispatch only those segments of the Resource's Incremental Energy Bids above the forecasted Host Load and subject to the Injection Limit.

The ISO will select the least cost mix of Ancillary Services and Energy from Suppliers, Demand Side Resources, and Customers submitting Virtual Transactions bids. The ISO may substitute higher quality Ancillary Services (*i.e.*, shorter response time) for lower quality Ancillary Services when doing so would result in an overall least bid cost solution. For example, 10-Minute Non-Synchronized Reserve may be substituted for 30-Minute Reserve if doing so would reduce the total bid cost of providing Energy and Ancillary Services.

#### **4.2.3.1 Reliability Forecast for the Dispatch Day**

At the request of a Transmission Owner to meet the reliability of its local system, the ISO may incorporate into the ISO's Security Constrained Unit Commitment constraints specified by the Transmission Owner.

A Transmission Owner may request commitment of certain Generators for a Dispatch Day if it determines that certain Generators are needed to meet the reliability of its local system. Such request shall be made before the Day-Ahead Market for that Dispatch Day has closed if the Transmission Owner knows of the need to commit certain Generators before the Day-Ahead Market close. The ISO may commit one or more Generator(s) in the Day-Ahead Market for a Dispatch Day if it determines that the Generator(s) are needed to meet NYCA reliability requirements.

A Transmission Owner may request commitment of additional Generators for a Dispatch Day following the close of the Day-Ahead Market to meet changed or local system conditions for the Dispatch Day that may cause the Day-Ahead schedules for the Dispatch Day to be

inadequate to ensure the reliability of its local system. The ISO will use SRE to fulfill a Transmission Owner's request for additional units.

All Generator commitments made in the Day-Ahead Market pursuant to this Section 4.2.3.1 shall be posted on the ISO website following the close of the Day-Ahead Market, in accordance with ISO procedures. In addition, the ISO shall post on its website a non-binding, advisory notification of a request, or any modifications thereto, made pursuant to this Section 4.2.3.1 in the Day-Ahead Market by a Transmission Owner to commit a Generator that is located within a Constrained Area, as defined in Attachment H of this Services Tariff. The advisory notification shall be provided upon receipt of the request and in accordance with ISO procedures. The postings described here may be included with the operator-initiated commitment report that the ISO posts in accordance with Section 4.1.3.4 of this Services Tariff.

After the Day-Ahead schedule is published, the ISO shall evaluate any events, including, but not limited to, the loss of significant Generators or transmission facilities that may cause the Day-Ahead schedules to be inadequate to meet the Load or reliability requirements for the Dispatch Day.

In order to meet Load or reliability requirements in response to such changed conditions the ISO may: (i) commit additional Resources, beyond those committed Day-Ahead, using a SRE and considering (a) Bids submitted to the ISO that were not previously accepted but were designated by the bidder as continuing to be available; or (b) new Bids from all Suppliers, including neighboring systems; or (ii) take the following actions: (a) after providing notice, require all Resources to run above their  $UOL_{NS}$ , up to the level of their  $UOL_{ES}$  (pursuant to ISO Procedures) and/or raise the  $UOL_{NS}$  of Capacity Limited Resources and Energy Limited Resources to their  $UOL_E$  levels, or (b) cancel or reschedule transmission facility maintenance

outages when possible. Actions taken by the ISO in performing supplemental commitments will not change any financial commitments that resulted from the Day-Ahead Market.

#### **4.2.4 Reliability Forecast for the Six Days Following the Dispatch Day**

In the SCUC program, system operation shall be optimized based on Bids over the Dispatch Day. However, to preserve system reliability, the ISO must ensure that there will be sufficient resources available to meet forecasted Load and reserve requirements over the seven (7)-day period that begins with the next Dispatch Day. The ISO will perform a Supplemental Resource Evaluation (“SRE”) for days two (2) through seven (7) of the commitment cycle. If it is determined that a long start-up time Generator (*i.e.*, a Generator that cannot be scheduled by SCUC to start up in time for the next Dispatch Day) is needed for reliability, the ISO shall accept a Bid from the Generator and the Generator will begin its start-up sequence. During each day of the start-up sequence, the ISO will perform an SRE to determine if long start-up time Generators will still be needed as previously forecasted. If at any time it is determined that the Generator will not be needed as previously forecasted, the ISO shall order the Generator to abort its start-up sequence.

The ISO will commit to long start-up time Generators to preserve reliability. However, the ISO will not commit resources with long start-up times to reduce the cost of meeting Loads that it expects to occur in days following the next Dispatch Day.

A Supplier that bids on behalf of a long start-up time Generator, including one that is committed and whose start is subsequently aborted by the ISO as described in this Section 4.2.4, may be eligible for a Bid Production Cost Guarantee pursuant to the provisions of Section 4.6.6 and Attachment C of this ISO Services Tariff. The costs of such a Bid Production Cost guarantee will be recovered by the ISO under Rate Schedule 1 of the ISO OATT.

The ISO shall perform the SRE as follows: (1) The ISO shall develop a forecast of daily system peak Load for days two (2) through seven (7) in this seven (7)-day period and add the appropriate reserve margin; (2) the ISO shall then forecast its available Generators for the day in question by summing the Operating Capacity for all Generators currently in operation that are available for the commitment cycle, the Operating Capacity of all other Generators capable of starting on subsequent days to be available on the day in question, and an estimate of the net Imports from External Bilateral Transactions; (3) if the forecasted peak Load plus reserves exceeds the ISO's forecast of available Generators for the day in question, then the ISO shall commit additional Generators capable of starting prior to the day in question (*e.g.*, start-up period of two (2) days when looking at day three (3)) to assure system reliability; (4) in choosing among Generators with comparable start-up periods, the ISO shall schedule Generators to minimize Minimum Generation Bid and Start-Up Bid costs of meeting forecasted peak Load plus Ancillary Services consistent with the Reliability Rules; (5) in determining the appropriate reserve margin for days two (2) through seven (7), the ISO will supplement the normal reserve requirements to allow for forced outages of the short start-up period units (*e.g.*, gas turbines) assumed to be operating at maximum output in the unit commitment analysis for reliability.

Energy Bids are binding for day one (1) only for units in operation or with start-up periods less than one (1) day. Minimum Generation Bids for Generators with start-up periods greater than one (1) day will be binding only for units that are committed by the ISO and only for the first day in which those units could produce Energy given their start-up periods. For example, Minimum Generation Bids for a Generator with a start-up period of two (2) days would be binding only for day three (3) because, if that unit begins to start up at any time during day one (1), it would begin to produce Energy forty-eight (48) hours later on day three (3).

Similarly, the Minimum Generation Bids for a Generator with a start-up period of three (3) days would be binding only for day four (4).

#### **4.2.5 Post the Day-Ahead Schedule**

By 11 a.m. on the day prior to the Dispatch Day, the ISO shall close the Day-Ahead scheduling process and post on the Bid/Post System the Day-Ahead schedule for each entity that submits a Bid or Bilateral Transaction schedule. All schedules shall be considered proprietary, with the posting only visible to the appropriate scheduling Customer and Transmission Owners subject to the applicable Code of Conduct (See Attachment F to the ISO OATT). The ISO will post on the OASIS the statewide aggregate resources (Day-Ahead Energy schedules and total operating capability forecast), Day-Ahead scheduled Load, forecast Load for each Load Zone, and the Day-Ahead LBMP prices (including the Congestion Component and the Marginal Losses Component) for each Load Zone in each hour of the upcoming Dispatch Day. The ISO shall conduct the Day-Ahead Settlement based upon the Day-Ahead schedule determined in accordance with this section and Attachment B to this Services Tariff. The ISO will provide the Transmission Owner with the Load forecast (for seven (7) days) as well as the ISO security evaluation data to enable local area reliability to be assessed.

#### **4.2.6 Day-Ahead LBMP Market Settlements**

The ISO shall calculate the Day-Ahead LBMPs for each Load Zone and at each Generator bus and Demand Reduction Bus as described in Attachment B. Each Supplier that bids a Generator into the ISO Day-Ahead Market and is scheduled in the SCUC to sell or purchase Energy in the Day-Ahead Market will be settled at the product of: (a) the Day-Ahead hourly LBMP at the applicable Generator bus; and (b) the hourly Energy schedule. Each Supplier that bids an External Transaction into the Day-Ahead LBMP Market and is scheduled in

the SCUC to sell Energy into the Day-Ahead LBMP Market will be settled at the product of (a) the Day-Ahead LBMP at the applicable Proxy Generator Bus and (b) the External Transaction schedule. For each Demand Reduction Provider that bids a Demand Reduction into the Day-Ahead Market and is scheduled in SCUC to provide Energy from the Demand Reduction, the LSE providing Energy service to the Demand Side Resource that accounts for the Demand Reduction shall be settled at the product of: (a) the Day-Ahead hourly LBMP at the applicable Demand Reduction Bus; and (b) the hourly demand reduction scheduled Day-Ahead (in MW).

In addition, each Demand Reduction Provider that bids a Demand Reduction into the Day-Ahead Market and is scheduled in the SCUC to provide Energy through Demand Reduction shall receive a Demand Reduction Incentive Payment from the ISO equal to the product of: (a) the Day-Ahead hourly LBMP at the Demand Reduction bus; and (b) the lesser of the verified actual hourly Demand Reduction or the scheduled hourly Demand Reduction (in MW). Each Customer that bids into the Day-Ahead Market, including each Customer that submits a Bid for a Virtual Transaction, and has a schedule accepted by the ISO to purchase Energy in the Day-Ahead Market will pay the product of: (a) the Day-Ahead hourly Zonal LBMP at each Point of Withdrawal; and (b) the scheduled Energy at each Point of Withdrawal. Each Supplier that bids an External Transaction into the Day-Ahead LBMP Market and is scheduled in the SCUC to buy Energy from the Day-Ahead LBMP Market will pay the product of (a) the Day-Ahead LBMP at the applicable Proxy Generator Bus and (b) the External Transaction schedule. Each Customer that submits a Virtual Transaction bid into the ISO Day-Ahead Market and has a schedule accepted by the ISO to sell Energy in a Load Zone in the Day-Ahead Market will receive a payment equal to the product of (a) the Day-Ahead hourly zonal LBMP for that Load Zone; and (b) the hourly scheduled Energy for the Customer in that Load Zone. Each Trading Hub Energy

Owner who bids a Bilateral Transaction into the Day-Ahead Market with a Trading Hub as its POI and has its schedule accepted by the ISO will pay the product of: (a) the Day-Ahead hourly zonal LBMP for the Load Zone associated with that Trading Hub; and (b) the Bilateral Transaction scheduled MW. Each Trading Hub Energy Owner who bids a Bilateral Transaction into the Day-Ahead Market with a Trading Hub as its POW and has its schedule accepted by the ISO will be paid the product of: (a) the Day-Ahead hourly zonal LBMP for the Load Zone associated with that Trading Hub; and (b) the Bilateral Transaction scheduled MW.

The ISO shall publish the Day-Ahead Settlement Load Zone LBMPs for each hour in the Dispatch Day.

## **5.12 Requirements Applicable to Installed Capacity Suppliers**

### **5.12.1 Installed Capacity Supplier Qualification Requirements**

In order to qualify as an Installed Capacity Supplier, Generators and controllable transmission projects electrically located in the NYCA, and transmission projects with associated incremental transfer capability, must have obtained Capacity Resource Interconnection Service (“CRIS”) pursuant to the applicable provisions of Attachment S to the ISO OATT and have entered service: controllable transmission projects must also have obtained Unforced Capacity Deliverability Rights and transmission projects with associated incremental transfer capability must also have obtained External-to-ROS Deliverability Rights. Even if a Generator has otherwise satisfied the requirements to participate in the ISO’s Installed Capacity market, a Generator in Inactive Reserves, an ICAP Ineligible Forced Outage, a Mothball Outage, or that is Retired is ineligible to participate in the ISO’s Installed Capacity market. A Generator that elects to participate in the ICAP Market, and is within a defined electrical boundary, electrically interconnected with, and routinely serves a Host Load (which Host Load does not consist solely of Station Power) at a single PTID can only participate in the Installed Capacity market as a Behind-the-Meter Net Generation Resource.

In addition, to qualify as an Installed Capacity Supplier in the NYCA, Energy Limited Resources, Generators, Installed Capacity Marketers, Intermittent Power Resources, Behind-the-Meter Net Generation Resources, Limited Control Run-of-River Hydro Resources and System Resources rated 1 MW or greater, other than External System Resources and Control Area System Resources which have agreed to certain Curtailment conditions as set forth in the third to last paragraph of Section 5.12.1 below, Responsible Interface Parties, existing municipally-owned generation, Energy Limited Resources, and Intermittent Power Resources, to the extent

those entities are subject to the requirements of Section 5.12.11 of this Tariff, and Energy Storage Resources with a nameplate capacity rating that allows a minimum injection to the NYS Transmission System or distribution system of 0.1 MW or greater shall:

- 5.12.1.1 provide information reasonably requested by the ISO including the name and location of Generators, and System Resources;
- 5.12.1.2 in accordance with the ISO Procedures, perform DMNC or DMGC tests and submit the results to the ISO, or provide to the ISO appropriate historical production data;
- 5.12.1.3 abide by the ISO Generator maintenance coordination procedures;
- 5.12.1.4 provide the expected return date from any outages (including partial outages) to the ISO;
- 5.12.1.5 in accordance with the ISO Procedures,
  - 5.12.1.5.1 provide documentation demonstrating that it will not use the same Unforced Capacity for more than one (1) buyer at the same time, and
  - 5.12.1.5.2 in the event that the Installed Capacity Supplier supplies more Unforced Capacity than it is qualified to supply in any specific month (*i.e.*, is short on Capacity), documentation that it has procured sufficient Unforced Capacity to cover this shortfall.
- 5.12.1.6 except for Installed Capacity Marketers and Intermittent Power Resources that depend upon wind or solar as their fuel, Bid into the Day-Ahead Market, unless the Energy Limited Resource, Generator, Limited Control Run-of-River Hydro Resource or System Resource is unable to do so due to an outage as defined in the ISO Procedures or due to temperature related de-ratings.

Generators may also enter into the MIS an upper operating limit that would define the operating limit under normal system conditions. The circumstances under which the ISO will direct a Generator to exceed its upper operating limit are described in the ISO Procedures;

5.12.1.7 provide Operating Data in accordance with Section 5.12.5 of this Tariff;

5.12.1.8 provide notice to the ISO of any proposed transfers of deliverability rights to be carried out pursuant to Sections 25.9.4 - 25.9.6 of Attachment S to the ISO OATT, on the Class Year Start Date if a request to transfer CRIS at a different location, and upon the submission of the request if it is a request to transfer CRIS at the same location;

5.12.1.9 comply with the ISO Procedures;

5.12.1.10 when the ISO issues a Supplemental Resource Evaluation request (an SRE), NYCA Resources must Bid into the in-day market unless (and only to the extent) the entity has a bid pending in the Real-Time Market when the SRE request is made or is unable to bid in response to the SRE request due to an outage as defined in the ISO Procedures, or due to other operational issues, or due to temperature related deratings.

If an External Installed Capacity Supplier is a Generator, or if an External Generator is associated with an Unforced Capacity sale using UDRs or EDRs, then except to the extent such a Generator is unable to Bid in response to the SRE request due to an outage as defined in the ISO Procedures, due to physical operating limitations affecting the Generator, or due to other operational issues that are outside the Installed Capacity Supplier's control, as determined by the

ISO, it must take all of the following actions for each hour of an SRE request

- (a) Bid an Import to the NYCA in a MW quantity equal to the lesser of (i) the ICAP equivalent of the UCAP sold, or (ii) the maximum MW the Generator is able to produce, at the approved Proxy Generator Bus, at the applicable minimum Bid Price, and
- (b) ensure that the External Generator is operating and is available to provide all of the MW that were Bid to be imported into the NYCA, up to the ICAP equivalent of the UCAP sold, for the entire duration of the SRE request, and
- (c) obtain all reservations and transmission service necessary to deliver all of the MW that were Bid to be imported into the NYCA or to a Locality from the Generator, up to the ICAP equivalent of the UCAP sold from the External Generator, at the approved Proxy Generator Bus.

If the External Installed Capacity Supplier that is a Generator, or the External Generator associated with an Unforced Capacity sale using UDRs or EDRs, is not able to Import the quantity of Energy equal to the ICAP equivalent of the UCAP sold from the Generator or EDR to the NYCA, or if a UDR to the Locality, for every hour of an SRE request then, except to the extent already addressed by a declared outage, the Generator shall provide to the ISO an explanation of the reasons for its failure or inability to perform, including evidence demonstrating any physical operating limitations or other operational issues that prevented the Generator from Importing the quantity of Energy equal to the ICAP equivalent of the UCAP sold from the Generator to the NYCA. To the extent the ISO determines that the information and supporting evidence provided demonstrates that the failure or inability to deliver occurred for reasons

outside the control of the External Installed Capacity Supplier or the External Generator associated with an Unforced Capacity sale using UDRs or EDRs, then the deficiency charge set forth in Section 5.12.12.2 below that applies solely to violations of this Section 5.12.1.10, shall not be assessed.

If an External Installed Capacity Supplier is a Control Area System Resource then, except to the extent it is unable to Bid in response to the SRE request due to an outage as defined in the ISO Procedures or due to operational issues that are outside the Installed Capacity Supplier's control, it must take all of the following actions for each hour of an SRE request (x) Bid an Import in a MW quantity equal to the ICAP equivalent of the UCAP sold, at the approved Proxy Generator Bus, at the applicable minimum Bid Price, and (y) obtain all reservations and transmission service necessary to deliver the ICAP equivalent of the UCAP sold from the Control Area System Resource to the NYCA at the approved Proxy Generator Bus.

If the External Installed Capacity Supplier that is a Control Area System Resource is not able to Import the quantity of Energy equal to the ICAP equivalent of the UCAP sold from the Control Area System Resource to the NYCA for every hour of an SRE request then, except to the extent already addressed by a declared outage, the External Installed Capacity Supplier shall provide to the ISO an explanation of the reasons for its failure or inability to perform, including evidence demonstrating any operational issues that prevented the External ICAP Supplier from Importing the quantity of Energy equal to the ICAP equivalent of the UCAP sold from the Control Area System Resource to the

NYCA. To the extent the ISO determines that the information and supporting evidence provided demonstrates that the failure or inability to deliver occurred for reasons outside the External Installed Capacity Supplier's control, then the deficiency charge set forth in Section 5.12.12.2 below that applies solely to violations of this Section 5.12.1.10, shall not be assessed. A Control Area System Resource must demonstrate that transmission outage(s) prevented delivery of all available Resources in order for the ISO to determine that the Control Area System Resource's failure to Import the quantity of Energy equal to the ICAP equivalent of the UCAP sold occurred for a reason that was outside the External Installed Capacity Supplier's control.

When an External Installed Capacity Supplier that is responding to an ISO SRE request Bids its Import at a Non-Competitive Proxy Generator Bus, its obligation to Bid an Import at the applicable minimum Bid Price includes the obligation to ensure that neither the External Installed Capacity Supplier nor any of its Affiliates are offering other Imports at an equivalent or greater economic priority at the Non-Competitive Proxy Generator Bus.

5.12.1.11 Installed Capacity Suppliers located East of Central-East shall Bid in the Day-Ahead and Real-Time Markets all Capacity available for supplying 10-Minute Non-Synchronized Reserve (unless the Generator is unable to meet its commitment because of an outage as defined in the ISO Procedures), except for the Generators described in Subsections 5.12.1.11.1, 5.12.1.11.2 and 5.12.1.11.3 below;

- 5.12.1.11.1 Generators providing Energy under contracts executed and effective on or before November 18, 1999 (including PURPA contracts) in which the power purchasers do not control the operation of the supply source but would be responsible for penalties for being off-schedule, with the exception of Generators under must-take PURPA contracts executed and effective on or before November 18, 1999, who have not provided telemetering to their local TO and historically have not been eligible to participate in the NYPP market, which will continue to be treated as TO Load modifiers under the ISO-administered markets;
- 5.12.1.11.2 Existing topping turbine Generators and extraction turbine Generators producing Energy resulting from the supply of steam to the district steam system located in New York City (LBMP Zone J) in operation on or before November 18, 1999 and/or topping or extraction turbine Generators used in replacing or repowering steam supplies from such units (in accordance with good engineering and economic design) that cannot follow schedules, up to a maximum total of 523 MW of such units; and
- 5.12.1.11.3 Units that have demonstrated to the ISO that they are subject to environmental, contractual or other legal or physical requirements that would otherwise preclude them from providing 10-Minute NSR.
- 5.12.1.12 A Resource that was determined by the ISO to be qualified as a Behind-the-Meter Net Generation Resource and for which Net Unforced Capacity was calculated by the ISO for a Capability Year can annually, by written notice received by the NYISO prior to August 1, elect not to participate in the ISO Administered Markets as a Behind-the-Meter Net Generation Resource. Such

notice shall be in accordance with ISO Procedures. A Resource that makes such an election cannot participate as a Behind-the-Meter Net Generation Resource for the entire Capability Year for which it made the election, but can, however, prior to August 1 of any subsequent Capability Year, provide all required information in order to seek to re-qualify as a Behind-the-Meter Net Generation Resource.

5.12.1.13 For Energy Storage Resources, be capable of running for a minimum of four (4) consecutive hours each day (except for days when it is not capable of doing so because of an outage reported pursuant to Sections 5.12.3, 5.12.5.3, 5.12.5.4, 5.12.7 and in accordance with ISO Procedures), ~~and elect the ISO-Managed Energy Level bidding parameter for each Day Ahead Market Bid.~~ An Energy Storage Resource may de-rate its maximum capability in order to meet the four (4) consecutive hour run-time requirement. ESRs electing to de-rate their maximum capability shall perform a DMNC test at an output level consistent with its de-rated capability in accordance with ISO Procedures (see, Installed Capacity Manual § 4).

The ISO shall inform each potential Installed Capacity Supplier that the ISO must receive and approve DMNC or DMGC data, as applicable of its approved DMNC or DMGC ratings for the Summer Capability Period and the Winter Capability Period in accordance with the ISO Procedures.

Requirements to qualify as Installed Capacity Suppliers for External System Resources and Control Area System Resources located in External Control Areas that have agreed not to Curtail the Energy associated with such Installed Capacity or to afford it the same Curtailment priority that it affords its own Control Area Load shall be established in the ISO Procedures.

External Installed Capacity not associated with UDRs, including capacity associated with External CRIS Rights, EDRs, Grandfathered External Installed Capacity Agreements listed in Attachment E of the ISO Installed Capacity Manual, the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation in Table 3 of Attachment L to the ISO OATT, Import Rights, and External System Resources, is only qualified to satisfy a NYCA Minimum Unforced Capacity Requirement and is not eligible to satisfy a Locational Minimum Installed Capacity Requirement.

Not later than 30 days prior to each ICAP Spot Market Auction, each Market Participant that may make offers to sell Unforced Capacity in such auction shall submit information to the ISO, in accordance with ISO Procedures and in the format specified by the ISO that identifies each Affiliated Entity, as that term is defined in Section 23.2.1 of Attachment H of the Services Tariff, of the Market Party or with which the Market Party is an Affiliated Entity. The names of entities that are Affiliated Entities shall not be treated as Confidential Information, but such treatment may be requested for the existence of an Affiliated Entity relationship. The information submitted to the ISO shall identify the nature of the Affiliated Entity relationship by the applicable category specified in the definition of “Affiliated Entity” in Section 23.2.1 of Attachment H of the Services Tariff.

#### **5.12.2 Additional Provisions Applicable to External Installed Capacity Suppliers**

Terms in this Section 5.12.2 not defined in the Services Tariff have the meaning set forth in the OATT.

##### **5.12.2.1 Provisions Addressing the Applicable External Control Area**

External Generators, External System Resources, and Control Area System Resources qualify as Installed Capacity Suppliers if they demonstrate to the satisfaction of the NYISO that

the Installed Capacity Equivalent of their Unforced Capacity is deliverable to the NYCA; in the case of an entity using a UDR to meet a Locational Minimum Installed Capacity Requirement, to the NYCA interface associated with that UDR transmission facility and will not be recalled or curtailed by an External Control Area to satisfy its own Control Area Loads; in the case of an EDR, to the NYCA interface over which it creates increased transfer capability; and in the case of Control Area System Resources, if they demonstrate that the External Control Area will afford the NYCA Load the same curtailment priority that they afford their own Control Area Native Load Customers. The amount of Unforced Capacity that may be supplied by such entities qualifying pursuant to the alternative criteria may be reduced by the ISO, pursuant to ISO Procedures, to reflect the possibility of curtailment. External Installed Capacity associated with Import Rights, EDRs or UDRs is subject to the same deliverability requirements applied to Internal Installed Capacity Suppliers associated with UDRs.

#### **5.12.2.2 Additional Provisions Addressing Internal Deliverability and Import Rights**

In addition to the provisions contained in Section 5.12.2.1 above, External Installed Capacity not associated with UDRs, EDRs, or External CRIS Rights will be subject to the deliverability test in Section 25.7.8 and 25.7.9 of Attachment S to the ISO OATT. The deliverability of External Installed Capacity not associated with UDRs, EDRs, or External CRIS Rights will be evaluated annually as a part of the process that sets import rights for the upcoming Capability Year, to determine the amount of External Installed Capacity that can be imported to the New York Control Area across any individual External Interface and across all of those External Interfaces, taken together. The External Installed Capacity deliverability test will be performed using the ISO's forecast, for the upcoming Capability Year, of New York Control Area CRIS resources, transmission facilities, and load. Under this process (i) Grandfathered

External Installed Capacity Agreements listed in Attachment E of the ISO Installed Capacity Manual, and (ii) the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation in Table 3 of Attachment L to the ISO OATT, will be considered deliverable within the Rest of State. Additionally, 1090 MW of imports made over the Quebec (via Chateauguay) Interface will be considered to be deliverable until the end of the 2010 Summer Capability Period.

The import limit set for External Installed Capacity not associated with UDRs, EDRs or External CRIS Rights will be set no higher than the amount of imports deliverable into Rest of State that (i) would not increase the LOLE as determined in the upcoming Capability Year IRM consistent with Section 2.7 of the NYISO Installed Capacity Manual, "Limitations on Unforced Capacity Flow in External Control Areas," (ii) are deliverable within the Rest of State Capacity Region when evaluated with the New York Control Area CRIS resources (including EDRs and UDRs) and External CRIS Rights forecast for the upcoming Capability Year, and (iii) would not degrade the transfer capability of any Other Interface by more than the threshold identified in Section 25.7.9 of Attachment S to the ISO OATT. Import limits set for External Installed Capacity will reflect the modeling of awarded External CRIS rights, but the awarded External CRIS rights will not be adjusted as part of import limit-setting process. Procedures for qualifying selling, and delivery of External Installed Capacity are detailed in the Installed Capacity Manual.

Until the grandfathered import rights over the Quebec (via Chateauguay) Interface expire at the end of the 2010 Summer Capability Period, the 1090 MW of grandfathered import rights will be made available on a first-come, first-served basis pursuant to ISO Procedures. Any of the grandfathered import rights over the Quebec (via Chateauguay) Interface not utilized for a

Capability Period will be made available to other external resources for that Capability Period, pursuant to ISO Procedures, to the extent the unutilized amount is determined to be deliverable.

Additionally, any of the Existing Transmission Capacity for Native Load listed for New York State Electric & Gas Corporation not utilized by New York State Electric & Gas Corporation for a Capability Period will be made available to other external resources for that Capability Period, pursuant to ISO procedures, to the extent the unutilized amount is determined to be deliverable within the Rest of State Capacity Region.

LSEs with External Installed Capacity as of the effective date of this Tariff will be entitled to designate External Installed Capacity at the same NYCA Interface with another Control Area, in the same amounts in effect on the effective date of this Tariff. To the extent such External Installed Capacity corresponds to Existing Transmission Capacity for Native Load as reflected in Table 3 of Attachment L to the ISO OATT, these External Installed Capacity rights will continue without term and shall be allocated to the LSE's retail access customers in accordance with the LSE's retail access program on file with the PSC and subject to any necessary filings with the Commission. External Installed Capacity rights existing as of September 17, 1999 that do not correspond to Table 3 of Attachment L to the ISO OATT shall survive for the term of the relevant External Installed Capacity contract or until the relevant External Generator is retired.

#### **5.12.2.3 One-Time Conversion of Grandfathered Quebec (via Chateauguay) Interface Rights.**

An entity can request to convert a specified number of MW, up to 1090 MW over the Quebec External Interface (via Chateauguay), into External CRIS Rights by making either a Contract Commitment or Non-Contract Commitment that satisfies the requirements of Section 25.7.11.1 of Attachment S to the ISO OATT. The converted number of MW will not be

subject to further evaluation for deliverability within a Class Year Deliverability Study under Attachment S to the ISO OATT, as long as the External CRIS Rights are in effect.

5.12.2.3.1 The External CRIS Rights awarded under this conversion process will first become effective for the 2010-2011 Winter Capability Period.

5.12.2.3.2 Requests to convert these grandfathered rights must be received by the NYISO on or before 5:00 pm Eastern Time on February 1, 2010, with the following information: (a) a statement that the entity is electing to convert by satisfying the requirements of a Contract Commitment or a Non-Contract Commitment in accordance with Section 25.7.11.1 of Attachment S to the ISO OATT; (b) the length of the commitment in years; (c) for the Summer Capability Period, the requested number of MW; (d) for the Winter Capability Period, the Specified Winter Months, if any, and the requested number of MW; and (e) a minimum number of MW the entity will accept if granted (“Specified Minimum”) for the Summer Capability Period and for all Specified Winter Months, if any.

5.12.2.3.3 An entity cannot submit one or more requests to convert in the aggregate more than 1090 MW in any single month.

5.12.2.3.4 If requests to convert that satisfy all other requirements stated herein are equal to or less than the 1090 MW limit, all requesting entities will be awarded the requested number of MW of External CRIS Rights. If conversion requests exceed the 1090 MW limit, the NYISO will prorate the allocation based on the weighted average of the requested MW times the length of the contract/commitment (*i.e.*, number of Summer Capability Periods) in accordance with the following formula:

$$\begin{aligned}
 & \text{Rights allocated to entity } i \\
 & = 1090 \\
 & * (MW_i * \text{contract/commitment length}_i) \\
 & / \sum_j (MW_j * \text{contract/commitment length}_j)
 \end{aligned}$$

$j = 1, \dots, \#$  entities requesting import rights

In the formula, contract/commitment length means the lesser of the requested contract/commitment length and twenty (20) years. The NYISO will perform separate calculations for the Summer and Winter Capability Periods. The NYISO will determine whether the prorated allocated number of MW for any requesting entity is less than the entity's Specified Minimum. If any allocation is less, the NYISO will remove such request(s) and recalculate the prorated allocations among the remaining requesting entities using the above formula. This process will continue until the prorated allocation meets or exceeds the specified minimum for all remaining requests.

5.12.2.3.5 Any portion of the previously grandfathered 1090 MW not converted through this process will no longer be grandfathered from deliverability. Previously grandfathered rights converted to External CRIS Rights but then terminated will no longer be grandfathered from deliverability.

#### **5.12.2.4 Offer Cap Applicable to Certain External CRIS Rights**

Notwithstanding any other capacity mitigation measures or obligations that may apply, the offers of External Installed Capacity submitted pursuant to a Non-Contract Commitment, as described in Section 25.7.11.1.2 of Attachment S of the ISO OATT, will be subject to an offer cap in each month of the Summer Capability Period and for all Specified Winter Months. This offer cap will be determined as the higher of:

5.12.2.4.1 1.1 times the price corresponding to all available Unforced Capacity determined from the NYCA ICAP Demand Curve for that Period; and

5.12.2.4.2 The most recent auction clearing price (a) in the External market supplying the External Installed Capacity, if any, and if none, then the most recent auction clearing price in an External market to which the capacity may be wheeled, less (b) any transmission reservation costs in the External market associated with providing the Installed Capacity, in accordance with ISO Procedures.

### **5.12.3 Installed Capacity Supplier Outage Scheduling Requirements**

All Installed Capacity Suppliers, except for Control Area System Resources and Responsible Interface Parties, that intend to supply Unforced Capacity to the NYCA shall submit a confidential notification to the ISO of their proposed outage schedules in accordance with the ISO Procedures. Transmission Owners will be notified of these and subsequently revised outage schedules. Based upon a reliability assessment, if Operating Reserve deficiencies are projected to occur in certain weeks for the upcoming calendar year, the ISO will request voluntary rescheduling of outages. In the case of Generators actually supplying Unforced Capacity to the NYCA, if voluntary rescheduling is ineffective, the ISO will invoke forced rescheduling of their outages to ensure that projected Operating Reserves over the upcoming year are adequate.

A Generator that refuses a forced rescheduling of its outages for any unit shall be prevented from supplying Unforced Capacity in the NYCA with that unit during any month where it undertakes such outages. The rescheduling process is described in the ISO Procedures.

A Generator that intends to supply Unforced Capacity in a given month that did not qualify as an Installed Capacity Supplier prior to the beginning of the Capability Period must

notify the ISO in accordance with the ISO Procedures so that it may be subject to forced rescheduling of its proposed outages in order to qualify as an Installed Capacity Supplier. A Supplier that refuses the ISO's forced rescheduling of its proposed outages shall not qualify as an Installed Capacity Supplier for that unit for any month during which it schedules or conducts an outage.

Outage schedules for External System Resources and Control Area System Resources shall be coordinated by the External Control Area and the ISO in accordance with the ISO Procedures.

#### **5.12.4 Required Certification for Installed Capacity**

- (a) Each Installed Capacity Supplier must confirm to the ISO, in accordance with ISO Procedures that the Unforced Capacity it has certified has not been sold for use in an External Control Area.
- (b) Each Installed Capacity Supplier holding rights to UDRs or EDRs from an External Control Area must confirm to the ISO, in accordance with ISO Procedures, that it will not use as self-supply or offer, and has not sold, Installed Capacity associated with the quantity of MW for which it has not made its one time capability adjustment year election pursuant to Section 5.11.4 (if applicable.)
- (c) On and after the execution of an RMR Agreement, and for the duration of its term, an RMR Generator shall not enter into any new agreement or extend any other agreement that impairs or otherwise diminishes its ability to comply with its obligation under an RMR Agreement, or that limits its ability to provide Energy, Capacity, or Ancillary Services directly to the ISO Administered Markets. An Interim Service Provider shall not enter into any new agreement or extend any

other agreement that limits its ability to provide Energy, Capacity, or Ancillary Services directly to the ISO Administered Markets or otherwise meet its obligations as an Interim Service Provider.

#### **5.12.5 Operating Data Reporting Requirements**

To qualify as Installed Capacity Suppliers in the NYCA, Resources shall submit to the ISO Operating Data in accordance with this Section 5.12.5 and the ISO Procedures. Resources that do not submit Operating Data in accordance with the following subsections and the ISO Procedures may be subject to the sanctions provided in Section 5.12.12.1 of this Tariff.

Resources that were not in operation on January 1, 2000 shall submit Operating Data to the ISO no later than one month after such Resources commence commercial operation, and in accordance with the ISO Procedures and the following subsections as applicable.

##### **5.12.5.1 Generators, System Resources, Energy Limited Resources, Energy storage Resources, Responsible Interface Parties, Intermittent Power Resources, Limited Control Run-of-River Hydro Resources and Municipally Owned Generation**

To qualify as Installed Capacity Suppliers in the NYCA, Generators, External Generators, System Resources, External System Resources, Energy Limited Resources, Responsible Interface Parties, Intermittent Power Resources, Limited Control Run-of-River Hydro Resources, Energy Storage Resources, and municipally owned generation or the purchasers of Unforced Capacity associated with those Resources shall submit GADS Data, data equivalent to GADS Data, or other Operating Data to the ISO in accordance with the ISO Procedures. Prior to the successful implementation of a software modification that allows gas turbines to submit multiple bid points, these units shall not be considered to be forced out for any hours that the unit was available at its base load capability in accordance with the ISO

Procedures. This section shall also apply to any Installed Capacity Supplier, External or Internal, using UDRs to meet Locational Minimum Installed Capacity Requirements.

#### **5.12.5.2 Control Area System Resources**

To qualify as Installed Capacity Suppliers in the NYCA, Control Area System Resources, or the purchasers of Unforced Capacity associated with those Resources, shall submit CARL Data and actual system failure occurrences data to the ISO each month in accordance with the ISO Procedures.

#### **5.12.5.3 Transmission Projects Granted Unforced Capacity Deliverability Rights**

An owner of a transmission project that receives UDRs must, among other obligations, submit outage data or other operational information in accordance with the ISO procedures to allow the ISO to determine the number of UDRs associated with the transmission facility.

#### **5.12.5.4 Transmission Projects Granted External-to ROS Deliverability Rights**

An owner of a transmission project that receives EDRs must, among other obligations, submit outage data or other operational information when determined applicable by the ISO and in accordance with ISO Procedures.

### **5.12.6 Capacity Calculations, Operating Data Default, Value and Collection**

#### **5.12.6.1 ICAP Calculation for Behind-the-Meter Net Generation Resources**

The ISO shall calculate the amount of Net-ICAP for each Behind-the-Meter Net Generation Resource as the Adjusted DMGC of the Generator of the Behind-the-Meter Net Generation Resource minus the Resource's Adjusted Host Load in accordance with this Tariff and ISO Procedures.

#### **5.12.6.1.1 Adjusted DMGC**

The ISO's calculation of the Adjusted DMGC of a Behind-the-Meter Net Generation Resource shall be the least of: (i) its DMGC for the Capability Period; (ii) its Adjusted Host Load plus its applicable Injection Limit; and (iii) its Adjusted Host Load plus the number of MW of CRIS it has obtained, as determined in accordance with OATT Section 25 (OATT Attachment S) and ISO Procedures.

If the Station Power of a Behind-the-Meter Net Generation Resource is separately metered from all other Load of the Resource, such that the Station Power Load can be independently measured and verified, the Generator of a Behind-the-Meter Net Generation Resource may elect to perform a DMNC Test instead of a DMGC Test pursuant to ISO Procedures. Such election must be made in writing to the ISO prior to the start of the DMNC Test Period.

If a Behind-the-Meter Net Generation Resource elects to take a DMNC Test, the Station Power measured during such DMNC Test shall not be included in the Resource's Host Load. A Behind-the-Meter Net Generation Resource's DMNC value for the Capability Period shall be used in lieu of a DMGC value in the calculation of the Resource's Adjusted DMGC for the purposes of Sections 5.12.6.1 and 5.12.6.2 of this Services Tariff.

#### **5.12.6.1.2 Adjusted Host Load**

A Behind-the-Meter Net Generation Resource's Adjusted Host Load shall be equal to the product of the Average Coincident Host Load multiplied by one plus the Installed Reserve Margin.

The Adjusted Host Load shall be calculated by the ISO on an annual basis prior to the start of the Summer Capability Period and in accordance with ISO Procedures, based upon the

Behind-the-Meter Net Generation Resource's Average Coincident Host Load for the prior Summer Capability Period and the Winter Capability Period before that.

#### **5.12.6.1.2.1 Average Coincident Host Load**

The ISO must receive the Behind-the-Meter Net Generation Resource's applicable metered Load data required to calculate an Average Coincident Host Load in accordance with ISO Procedures. The ISO shall compute the Average Coincident Host Load for each Capability Year (i) using the metered Host Load data for the applicable NYCA peak Load hours, except as provided below in this Section, and (ii) adjusted for weather normalization and Load growth as determined by the ISO in relation to developing the NYCA Minimum Installed Capacity Requirement in accordance with ISO Procedures.

For each Capability Year, the NYISO shall use the average of the highest twenty (20) one-hour peak Loads of the Host Load of the Behind-the-Meter Net Generation Resource that occur during the top forty (40) NYCA peak Load hours of the prior Summer Capability Period and the Winter Capability Period before that to calculate the Average Coincident Host Load.

If a facility meets the criteria to be, and has not previously been, a Behind-the-Meter Net Generation Resource, but does not have all of the appropriate meter data, its Average Coincident Host Load shall be a value forecasted by the Behind-the-Meter Net Generation Resource. The Behind-the-Meter Net Generation Resource's forecast shall be based on actual meter data, or if not available, billing data or other business data of the Host Load. An estimated Average Coincident Host Load can only be applicable to a Behind-the-Meter Net Generation Resource until actual data becomes available, but in any event no longer than three (3) consecutive Capability Years beginning with the Capability Year it is first an Installed Capacity Supplier.

#### **5.12.6.1.2.2 Determination of Adjusted Host Load**

After the ISO has calculated a Behind-the-Meter Net Generation Resource's Average Coincident Host Load, it shall then apply the NYCA Installed Reserve Margin. The Behind-the-Meter Net Generation Resource's Adjusted Host Load will be established by multiplying the Resource's Average Coincident Host Load for the Capability Year by the quantity of one plus the NYCA Installed Reserve Margin.

#### **5.12.6.2 UCAP Calculations**

The ISO shall calculate for each Resource the amount of Unforced Capacity that each Installed Capacity Supplier is qualified to supply in the NYCA in accordance with formulae provided in the ISO Procedures.

The amount of Unforced Capacity that each Generator, except for the Generator of a Behind-the-Meter Net Generation Resource, System Resource, Energy Limited Resource, Special Case Resource, and municipally-owned generation is authorized to supply in the NYCA shall be based on the ISO's calculations of individual Equivalent Demand Forced Outage Rates. The amount of Unforced Capacity that each Energy Storage Resource is authorized to supply in the NYCA shall be based on the individual availability of the Energy Storage Resource in the Real-Time Market and calculated by the ISO in accordance with ISO Procedures. Except as provided in Section 5.12.6.2.1 of this Services Tariff, this calculation shall not include hours in any month that the Energy Storage Resource was in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market. The amount of Unforced Capacity that each Control Area System Resource is authorized to supply in the NYCA shall be based on the ISO's calculation of each Control Area System Resource's availability. The amount of Unforced Capacity that each Intermittent Power Resource is

authorized to supply in the NYCA shall be based on the NYISO's calculation of the amount of capacity that the Intermittent Power Resource can reliably provide during system peak Load hours in accordance with ISO Procedures. Except as provided in Section 5.12.6.2.1 of this Services Tariff, this calculation shall not include hours in any month that the Intermittent Power Resource was in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market. The amount of Unforced Capacity that each Limited Control Run-of-River Hydro Resource is authorized to provide in the NYCA shall be determined separately for Summer and Winter Capability Periods as the rolling average of the hourly net Energy provided by each such Resource during the 20 highest NYCA integrated real-time load hours in each of the five previous Summer or Winter Capability Periods, as appropriate, stated in megawatts. Except as provided in Section 5.12.6.2.1 of this Services Tariff, for a Limited Control Run-of-River Hydro Resource in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market during one of the 20 highest NYCA integrated real-time load hours in any one of the five previous Summer or Winter Capability Periods, the ISO shall replace that Winter or Summer Capability Period, as appropriate, with the next most recent Winter or Summer Capability Period such that the rolling average of the hourly net Energy provided by each such Resource shall be calculated from the 20 highest NYCA integrated real-time load hours in the five most recent prior Summer or Winter Capability Periods in which the Resource was not in an outage state that precluded its eligibility to participate in the Installed Capacity market on one of the 20 highest NYCA integrated real-time load hours in that Capability Period.

The ISO shall calculate separate Summer and Winter Capability Period Unforced Capacity values for each Generator, System Resource, Special Case Resource, Energy Limited

Resource, and municipally owned generation and update them periodically using a twelve-month calculation in accordance with formulae provided in the ISO Procedures; provided, however, except as provided in Section 5.12.6.2.1 of this Services Tariff, for a Generator in an outage state that started on or after May 1, 2015 and that precluded its eligibility to participate in the Installed Capacity market at any time during any month from which GADS or other operating data would otherwise be used to calculate an individual Equivalent Demand Forced Outage Rate, the ISO shall replace such month's GADS or other operating data with GADS or other operating data from the most recent prior month in which the Generator was not in an outage state that precluded its eligibility to participate in the Installed Capacity market.

The ISO shall calculate separate Summer and Winter Capability Period Unforced Capacity values for Energy Storage Resource and update them seasonally as described in ISO Procedures.

The ISO shall calculate separate Summer and Winter Capability Period Unforced Capacity values for Intermittent Power Resources and update them seasonally as described in ISO Procedures.

The amount of Unforced Capacity that each Behind-the-Meter Net Generation Resource is authorized to supply in the NYCA shall be its Net-UCAP. Net-UCAP is the lesser of (i) the ISO's calculation of the Generator of the Behind-the-Meter Net Generation Resource Adjusted DMGC multiplied by one minus its Equivalent Demand Forced Outage Rate, and then decreased by its Adjusted Host Load translated into Unforced Capacity terms consistent with Section 5.11.1 of this Tariff, and (ii) the Resource's Net-ICAP.

#### **5.12.6.2.1 Exceptions**

A Generator returning to the Energy market after taking an outage that precluded its

participation in the Installed Capacity market and which returns with modifications to its operating characteristics determined by the ISO to be material and which, therefore, requires the submission of a new Interconnection Request will receive, as the initial derating factor for calculation of the Generator's Unforced Capacity upon its return to service, the derating factor it would have received as a newly connecting unit in lieu of a derating factor developed from unit-specific data. A Generator returning to the Energy market after taking an outage that precluded its participation in the Installed Capacity market and which, upon its return, uses as its primary fuel a fuel not previously used at the facility for any purpose other than for ignition purposes will receive, as the initial derating factor for calculation of the Generator's Unforced Capacity upon its return to service, the NERC class average derating factor in lieu of a derating factor developed from unit-specific data even if the modifications to allow use of a new primary fuel are not material and do not require the submission of a new Interconnection Request.

This Section 5.12.6.2.1 shall apply to a Generator returning to the Energy market after taking an outage that started on or after May 1, 2015 and that precluded its participation in the Installed Capacity market.

### **5.12.6.3 Default Unforced Capacity**

In its calculation of Unforced Capacity, the ISO shall deem a Resource to be completely forced out for each month for which the Resource has not submitted its Operating Data in accordance with Section 5.12.5 of this Tariff and the ISO Procedures. A Resource that has been deemed completely forced out for a particular month may submit new Operating Data, for that month, to the ISO at any time. The ISO will use such new Operating Data when calculating, in a timely manner in accordance with the ISO Procedures, a Unforced Capacity value for the Resource.

Upon a showing of extraordinary circumstances, the ISO retains the discretion to accept at any time Operating Data which have not been submitted in a timely manner, or which do not fully conform with the ISO Procedures.

#### **5.12.6.4 Exception for Certain Equipment Failures**

When a Generator, Special Case Resource, Energy Limited Resource, or System Resource is forced into an outage by an equipment failure that involves equipment located on the high voltage side of the electric network beyond the step-up transformer, and including such step-up transformer, the outage will not be counted for purposes of calculating that Resource's Equivalent Demand Forced Outage Rate.

#### **5.12.6.5 Unforced Capacity, Outage Data and Operational Information Associated with External-to-ROS Deliverability Rights**

The ISO shall calculate the availability of the External interface associated with each project granted EDRs, in accordance with ISO Procedures. The availability factor (percentage) of the interface will be used to reduce the amount of EDRs for which Unforced Capacity may be offered. This calculation is distinct from and in addition to the calculation the ISO performs for each Installed Capacity Resource qualified for use with EDRs.

#### **5.12.7 Availability Requirements**

Subsequent to qualifying, each Installed Capacity Supplier shall, except as noted in Section 5.12.11 of this Tariff, on a daily basis: (i) schedule a Bilateral Transaction; (ii) Bid Energy in each hour of the Day-Ahead Market in accordance with the applicable provisions of Section 5.12.1 of this Tariff; or (iii) notify the ISO of any outages. An RMR Generator can only schedule a Bilateral Transaction to the extent expressly authorized in its RMR Agreement. The total amount of Energy that an Installed Capacity Supplier schedules, bids, or declares to be

unavailable on a given day must equal or exceed the Installed Capacity Equivalent of the Unforced Capacity it supplies.

#### **5.12.8 Unforced Capacity Sales**

Each Installed Capacity Supplier will, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT, be authorized to supply an amount of Unforced Capacity during each Obligation Procurement Period, based on separate seasonal Unforced Capacity calculations performed by the ISO for the Summer and Winter Capability Periods. Unforced Capacity may be sold in six-month strips, or in monthly, or multi-monthly segments.

External Unforced Capacity (except External Installed Capacity associated with UDRs) may only be offered into Capability Period Auctions or Monthly Auctions for the Rest of State, and ICAP Spot Market Auctions for the NYCA, and may not be offered into a Locality for an ICAP Auction. Bilateral Transactions which certify External Unforced Capacity using Import Rights, EDRs, or External CRIS Rights may not be used to satisfy a Locational Minimum Unforced Capacity Requirement.

UCAP from an RMR Generator may only be offered into the ICAP Spot Market Auction, except and only to the extent that the RMR Agreement expressly permits the RMR Generator's UCAP to be certified in a Bilateral Transaction.

If an Energy Limited Resource's, Generator's, System Resource's or Control Area System Resource's DMNC rating, or the DMGC rating of a Generator of a Behind-the-Meter Net Generation Resource, if applicable, is determined to have increased during an Obligation Procurement Period, pursuant to testing procedures described in the ISO Procedures, the amount of Unforced Capacity that it shall be authorized to supply in that or future Obligation

Procurement Periods shall also be increased on a prospective basis in accordance with the schedule set forth in the ISO Procedures provided that it first has satisfied the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT.

New Generators and Generators that have increased their Capacity since the previous Summer Capability Period due to changes in their generating equipment may, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT, qualify to supply Unforced Capacity on a foregoing basis during the Summer Capability Period based upon a DMNC test, or the DMGC test of a Generator of a Behind-the-Meter Net Generation Resource, that is performed and reported to the ISO after March 1 and prior to the beginning of the Summer Capability Period DMNC Test Period. The Generator will be required to verify the claimed DMNC or DMGC rating by performing an additional test during the Summer DMNC Test Period. Any shortfall between the amount of Unforced Capacity supplied by the Generator for the Summer Capability Period and the amount verified during the Summer DMNC Test Period will be subject to deficiency charges pursuant to Section 5.14.2 of this Tariff. The deficiency charges will be applied to no more than the difference between the Generator's previous Summer Capability Period Unforced Capacity and the amount of Unforced Capacity equivalent the Generator supplied for the Summer Capability Period.

New Generators and Generators that have increased their Capacity since the previous Winter Capability Period due to changes in their generating equipment may, after satisfying the deliverability requirements set forth in the applicable provisions of Attachment X, Attachment Z and Attachment S to the ISO OATT, qualify to supply Unforced Capacity on a foregoing basis

during the Winter Capability Period based upon a DMNC test, or the DMGC test of a Generator of a Behind-the-Meter Net Generation Resource, that is performed and reported to the ISO after September 1 and prior to the beginning of the Winter Capability Period DMNC Test Period. The Generator will be required to verify the claimed DMNC or DMGC rating by performing an additional test during the Winter Capability Period DMNC Test Period. Any shortfall between the amount of Unforced Capacity certified by the Generator for the Winter Capability Period and the amount verified during the Winter Capability Period DMNC Test Period will be subject to deficiency charges pursuant to Section 5.14.2 of this Tariff. The deficiency charges will be applied to no more than the difference between the Generator's previous Winter Capability Period Unforced Capacity and the amount of Unforced Capacity equivalent the Generator supplied for the Winter Capability Period.

Any Installed Capacity Supplier, except as noted in Section 5.12.11 of this ISO Services Tariff, which fails on a daily basis to schedule, Bid, or declare to be unavailable in the Day-Ahead Market an amount of Unforced Capacity, expressed in terms of Installed Capacity Equivalent, that it certified for that day, rounded down to the nearest 0.1 MW, or rounded down to the nearest whole MW for an External Installed Capacity Supplier, is subject to sanctions pursuant to Section 5.12.12.2 of this Tariff. If an entity other than the owner of an Energy Limited Resource, Generator, System Resource, Behind-the-Meter Net Generation Resource, or Control Area System Resource that is providing Unforced Capacity is responsible for fulfilling bidding, scheduling, and notification requirements, the owner and that entity must designate to the ISO which of them will be responsible for complying with the scheduling, bidding, and notification requirements. The designated bidding and scheduling entity shall be subject to sanctions pursuant to Section 5.12.12.2 of this ISO Services Tariff.

### **5.12.9 Sales of Unforced Capacity by System Resources**

Installed Capacity Suppliers offering to supply Unforced Capacity associated with Internal System Resources shall submit for each of their Resources the Operating Data and DMNC testing data or historical data described in Sections 5.12.1 and 5.12.5 of this ISO Services Tariff in accordance with the ISO Procedures. Such Installed Capacity Suppliers will be allowed to supply the amount of Unforced Capacity that the ISO determines pursuant to the ISO Procedures to reflect the appropriate Equivalent Demand Forced Outage Rate. Installed Capacity Suppliers offering to sell the Unforced Capacity associated with System Resources may only aggregate Resources in accordance with the ISO Procedures.

### **5.12.10 Curtailment of External Transactions In-Hour**

All Unforced Capacity that is not out of service, or scheduled to serve the Internal NYCA Load in the Day-Ahead Market may be scheduled to supply Energy for use in External Transactions provided, however, that such External Transactions shall be subject to Curtailment within the hour, consistent with ISO Procedures. Such Curtailment shall not exceed the Installed Capacity Equivalent committed to the NYCA.

### **5.12.11 Responsible Interface Parties, Municipally-Owned Generation, Energy Limited Resources and Intermittent Power Resources**

#### **5.12.11.1 Responsible Interface Parties**

Responsible Interface Parties may qualify as Installed Capacity Suppliers, without having to comply with the daily bidding, scheduling, and notification requirements set forth in Section 5.12.7 of this Tariff, if their Special Case Resources are available to operate at the direction of the ISO in order to reduce Load from the NYS Transmission System and/or the distribution system for a minimum of four (4) consecutive hours each day, except for those

subject to operating limitations established by environmental permits, which will not be required to operate in excess of two (2) hours and which will be derated by the ISO pursuant to ISO Procedures to account for the Load serving equivalence of the hours actually available, following notice of the potential need to operate twenty-one (21) hours in advance if notification is provided by 3:00 P.M. ET, or twenty-four (24) hours in advance otherwise, and a notification to operate two (2) hours ahead. In order for a Responsible Interface Party to enroll an SCR that uses an eligible Local Generator, any amount of generation that can reduce Load from the NYS Transmission System and/or distribution system at the direction of the ISO that was produced by the Local Generator during the hour coincident with the NYCA or Locality peaks, upon which the LSE Unforced Capacity Obligation of the LSE that serves that SCR is based, must be accounted for when the LSE's Unforced Capacity Obligation for the upcoming Capability Year is established. Responsible Interface Parties must provide this generator data in accordance with ISO Procedures so that the ISO can adjust upwards the LSE Unforced Capacity Obligation to prevent double-counting.

Responsible Interface Parties supplying Unforced Capacity cannot offer the Demand Reduction associated with such Unforced Capacity in the Emergency Demand Response Program. A Resource with sufficient metering to distinguish MWs of Demand Reduction may participate as a Special Case Resource and in the Emergency Demand Response Program provided that the same MWs are not committed both as Unforced Capacity and to the Emergency Demand Response Program.

The ISO will have discretion, pursuant to ISO Procedures, to exempt Local Generators that are incapable of starting in two (2) hours from the requirement to operate on two (2) hours notification. Local Generators that can be operated to reduce Load from the NYS Transmission

System and/or distribution system at the direction of the ISO and Loads capable of being interrupted upon demand, that are not available on certain hours or days will be derated by the ISO, pursuant to ISO Procedures, to reflect the Load serving equivalence of the hours they are actually available.

Responsible Interface Parties must submit a Minimum Payment Nomination, in accordance with ISO Procedures. The ISO may request Special Case Resource performance from less than the total number of Special Case Resources within the NYCA or a Load Zone in accordance with ISO Procedures.

Local Generators that can be operated to reduce Load from the NYS Transmission System and/or distribution system at the direction of the ISO and Loads capable of being interrupted upon demand will be required to comply with verification and validation procedures set forth in the ISO Procedures. Such procedures will not require metering other than interval billing meters on customer Load or testing other than DMNC or sustained disconnect, as appropriate, unless agreed to by the customer, except that Special Case Resources not called to supply Energy in a Capability Period will be required to run a test once every Capability Period in accordance with the ISO Procedures.

Unforced Capacity supplied in a Bilateral Transaction by a Special Case Resource pursuant to this subsection may only be resold if the purchasing entity or the Installed Capacity Marketer has agreed to become a Responsible Interface Party and comply with the ISO notification requirements for Special Case Resources. LSEs and Installed Capacity Marketers may become Responsible Interface Parties and aggregate Special Case Resources and sell the Unforced Capacity associated with them in an ISO-administered auction if they comply with ISO notification requirements for Special Case Resources.

Responsible Interface Parties that were requested to reduce Load in any month shall submit performance data to the NYISO, within 75 days of each called event or test, in accordance with ISO Procedures. Failure by a Responsible Interface Party to submit performance data for any Special Case Resources required to respond to the event or test within the 75-day limit will result in zero performance attributed to those Special Case Resources for purposes of satisfying the Special Case Resource's capacity obligation as well as for determining energy payments. All performance data are subject to audit by the NYISO and its market monitoring unit. If the ISO determines that it has made an erroneous payment to a Responsible Interface Party, the ISO shall have the right to recover it either by reducing other payments to that Responsible Interface Parties or by resolving the issue pursuant to other provisions of this Services Tariff or other lawful means.

Provided the Responsible Interface Party supplies evidence of such reductions in 75 days, the ISO shall pay the Responsible Interface Party that, through their Special Case Resources, caused a verified Load reduction in response to (i) an ISO request to perform due to a forecast reserve shortage (ii) an ISO declared Major Emergency State, (iii) an ISO request to perform made in response to a request for assistance for Load relief purposes or as a result of a Local Reliability Rule, or (iv) a test called by the ISO, for such Load reduction, in accordance with ISO Procedures. Subject to performance evidence and verification, in the case of a response pursuant to clauses (i), (ii), of (iii) of this subsection, Suppliers that schedule Responsible Interface Parties shall be paid the zonal Real-Time LBMP for the period of requested performance or four (4) hours, whichever is greater, in accordance with ISO Procedures; provided, however, Special Case Resource Capacity shall settle Demand Reductions, in the interval and for the capacity for which Special Case Resource Capacity has been scheduled Day-Ahead to provide Operating

Reserves, Regulation Service or Energy, as being provided by a Supplier of Operating Reserves, Regulation Service or Energy.

In the event that a Responsible Interface Party's Minimum Payment Nomination for a Special Case Resource, for the number of hours of requested performance or the minimum four (4) hour period, whichever is greater, exceeds the LBMP revenue received, the Special Case Resource will be eligible for a Bid Production Cost Guarantee to make up the difference, in accordance with Section 4.23 of this Services Tariff and ISO Procedures; provided, however, the ISO shall set to zero the Minimum Payment Nomination for Special Case Resource Capacity in each interval in which such Capacity was scheduled Day-Ahead to provide Operating Reserves, Regulation Service or Energy. Subject to performance evidence and verification, in the case of a response pursuant to clause (iv) of this subsection, payment for participation in tests called by the ISO shall be equal to the zonal Real Time LBMP for the MWh of Energy reduced within the test period.

Transmission Owners that require assistance from enrolled Local Generators larger than 100 kW and Loads capable of being interrupted upon demand for Load relief purposes or as a result of a Local Reliability Rule, shall direct their requests for assistance to the ISO for implementation consistent with the terms of this section. Within Load Zone J, participation in response to an ISO request to perform made as a result of a request for assistance from a Transmission Owner for less than the total number of Special Case Resources, for Load relief purposes or as a result of a Local Reliability Rule, in accordance with ISO Procedures, shall be voluntary and the responsiveness of the Special Case Resource shall not be taken into account for performance measurement.

#### **5.12.11.1.1 Special Case Resource Average Coincident Load**

The ISO must receive from the Responsible Interface Party that enrolls a Special Case Resource, the applicable metered Load data required to calculate an ACL for that SCR as provided below and in accordance with ISO Procedures. The ACL shall be computed using the metered Load for the applicable Capability Period SCR Load Zone Peak Hours that indicates the Load consumed by each SCR that is supplied by the NYS Transmission System and/or distribution system and is exclusive of any generation produced by a Local Generator, other behind-the-meter generator, or other supply source located behind the SCR's meter, that served some of the SCR's Load.

Beginning with the Winter 2011-2012 Capability Period and thereafter, the ISO shall use the average of the highest twenty (20) one-hour peak Loads of the SCR taken from the Load data reported for the Capability Period SCR Load Zone Peak Hours during the Prior Equivalent Capability Period, and taking into account the resource's reported verified Load reduction in a Transmission Owner's demand response program in hours coincident with any of these hours, to create a SCR ACL baseline. In addition, beginning with the Summer 2014 Capability Period, the resource's verified Load reduction in either of the ISO's economic demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of the applicable Capability Period SCR Load Zone Peak Hours will be taken into account when creating the SCR ACL. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Capability Period SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the ACL for each hour during the Capability Period SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the

greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Capability Period SCR Load Zone Peak Hour and (b) the metered Load of the resource as reported by the RIP for the Capability Period SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is identified as being a Capability Period SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Capability Period SCR Load Zone Peak Hour, in accordance with the preceding sentence. The ISO will post to its website the Capability Period SCR Load Zone Peak Hours for each zone ninety (90) days prior to the beginning of the Capability Period for which the ACL will be in effect.

In the SCR enrollment file uploaded by the RIP each month within the Capability Period, among other required information, the RIP shall provide the SCR's metered Load values for the applicable Capability Period SCR Load Zone Peak Hours necessary to compute the ACL for each SCR.

The exception to this requirement to report the required metered Load data for the ACL, when enrolling a SCR prior to the Summer 2014 Capability Period, is if (i) the SCR has not previously been enrolled with the ISO and (ii) never had interval metering Load data for each month in the Prior Equivalent Capability Period needed to compute the SCR's ACL. Beginning with the Summer 2014 Capability Period, the exception to this requirement to report the required metered Load data for the ACL, is dependent upon one or more of the eligibility conditions for SCR enrollment with a Provisional ACL provided in Section 5.12.11.1.2 of this Services Tariff and ISO Procedures. For SCRs that meet the criteria to enroll with a Provisional ACL, the ISO

must receive from the RIP a Provisional ACL as provided in Section 5.12.11.1.2 of this Services Tariff and in accordance with ISO Procedures.

Beginning with the Summer 2014 Capability Period, in addition to the requirement for RIPs to report each SCR's metered Load values that occurred during the Capability Period SCR Load Zone Peak Hours, in accordance with this Services Tariff and ISO Procedures during the enrollment process, any qualifying increase in a SCR's Load that will be supplied by the NYS Transmission System and/or distribution system may be reported as an Incremental ACL, subject to the limitations and verification reporting requirements provided in Section 5.12.11.1.5 of this Services Tariff and in accordance with ISO Procedures. Incremental ACL values must be reported using the required enrollment file that may be uploaded by the RIP during each month's enrollment period. RIPs may not report Incremental ACL values for any SCRs that are enrolled in the Capability Period with a Provisional ACL.

A reduction in a SCR's Load that is supplied by the NYS Transmission System and/or distribution system and meets the criteria for a SCR Change of Status must be reported as a SCR Change of Status as provided by Section 5.12.11.1.3 of this Services Tariff and in accordance with ISO Procedures.

The ACL is the basis for the upper limit of ICAP, except in circumstances when the SCR has reported a SCR Change of Status or reported an Incremental ACL pursuant to Sections 5.12.11.1.3 and 5.12.11.1.5 of this Services Tariff. The basis for the upper limit of ICAP for a SCR that has experienced a SCR Change of Status or reported an Incremental ACL shall be the Net ACL.

#### **5.12.11.1.2 Use of a Provisional Average Coincident Load**

Prior to the Summer 2014 Capability Period, as provided in Section 5.12.11.1.1 of this Services Tariff, if a new Special Case Resource has not previously been enrolled with the ISO and never had interval billing meter data from the Prior Equivalent Capability Period, its Installed Capacity value shall be its Provisional Average Coincident Load for the Capability Period for which the new SCR is enrolled. The Provisional ACL may be applicable to a new SCR for a maximum of three (3) consecutive Capability Periods, beginning with the Capability Period in which the SCR is first enrolled.

Beginning with the Summer 2014 Capability Period, a SCR may be enrolled using a Provisional ACL in lieu of an ACL when one of the following conditions has been determined by the ISO to apply: (i) the SCR has not previously been enrolled with the ISO for the seasonal Capability Period for which the SCR enrollment with a Provisional ACL is intended, (ii) the SCR was enrolled with a Provisional ACL in the Prior Equivalent Capability Period and was required to report fewer than twenty (20) hours of metered Load verification data that correspond with the Capability Period SCR Load Zone Peak Hours based on the meter installation date of the SCR, (iii) the RIP attempting to enroll the SCR with a Provisional ACL is not the same RIP that enrolled the SCR in the Prior Equivalent Capability Period and interval billing meter data for the SCR from the Prior Equivalent Capability Period is not obtainable by the enrolling RIP and not available to be provided to the enrolling RIP by the ISO. The Provisional ACL may be applicable to a SCR for a maximum of three (3) consecutive Capability Periods when enrolled with the same RIP, beginning with the Capability Period in which the SCR is first enrolled by the RIP.

A SCR enrolled in the Capability Period with a Provisional ACL may not be enrolled by another RIP for the remainder of the Capability Period and the Provisional ACL value shall apply to the resource for the entire Capability Period for which the value is established.

The Provisional ACL is the RIP's forecast of the SCR's ACL and shall be the basis for the upper limit of ICAP for which the RIP may enroll the SCR during the Capability Period.

Any SCR enrolled with a Provisional ACL shall be subject to actual in-period verification. A Verified ACL shall be calculated by the ISO using the top twenty (20) one-hour peak Loads reported for the SCR from the Capability Period SCR Load Zone Peak Hours that are applicable to verify the Provisional ACL in accordance with ISO Procedures and taking into account the resource's reported verified Load reductions in a Transmission Owner's demand response program that are coincident with any of the applicable Capability Period SCR Load Zone Peak Hours. In addition, beginning with the Summer 2014 Capability Period, the resource's verified Load reduction in either of the ISO's economic demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of the applicable Capability Period SCR Load Zone Peak Hours will be taken into account when creating the SCR Verified ACL. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Capability Period SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the Verified ACL for each hour during the Capability Period SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Capability Period SCR Load Zone Peak

Hour and (b) the metered Load of the resource as reported by the RIP for the Capability Period SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is identified as being a Capability Period SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Capability Period SCR Load Zone Peak Hour, in accordance with the preceding sentence.

Following the Capability Period for which a resource with a Provisional ACL was enrolled, the RIP shall provide to the ISO the metered Load data required to compute the Verified ACL of the resource. The ISO shall compare the Provisional ACL to the Verified ACL to determine, after applying the applicable performance factor, whether the UCAP of the SCR had been oversold and whether a shortfall has occurred as provided under Section 5.14.2 of this Services Tariff. If the RIP fails to provide verification data required to compute the Verified ACL of the resource enrolled with a Provisional ACL by the deadline: (a) the Verified ACL of the resource shall be set to zero for each Capability Period in which the resource with a Provisional ACL was enrolled and verification data was not reported, and (b) the RIP may be subject to penalties in accordance with this Services Tariff.

### **5.12.11.1.3 Reporting a SCR Change of Load or SCR Change of Status**

#### **5.12.11.1.3.1 SCR Change of Load**

The Responsible Interface Party shall report any SCR Change of Load in accordance with ISO Procedures. The RIP is required to document the SCR Change of Load and when the total Load reduction for SCRs that have a SCR Change of Load within the same Load Zone is greater

than or equal to 5 MWs, the RIP shall report the SCR Change of Load for each SCR in accordance with ISO Procedures.

#### **5.12.11.1.3.2 SCR Change of Status**

The Responsible Interface Party shall report any SCR Change of Status in accordance with ISO Procedures. The ISO shall adjust the reported ACL of the SCR for a reported SCR Change of Status to the Net ACL, for all prospective months to which the SCR Change of Status is applicable. When a SCR Change of Status is reported under clause (i), (ii) or (iii) within the definition of a Qualified Change of Status Condition and the SCR has sold capacity, the SCR shall be evaluated for a potential shortfall under Section 5.14.2 of this Services Tariff. Failure by the RIP to report a SCR Change of Status shall be evaluated as a potential shortfall under Section 5.14.2 of this Service Tariff and evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

Beginning with the Summer 2014 Capability Period, SCRs that were required to perform in the first performance test in the Capability Period in accordance with ISO Procedures and that subsequently report or change a reported SCR Change of Status value after the first performance test in the Capability Period shall be required to demonstrate the performance of the resource against the Net ACL value in the second performance test in the Capability Period. The exceptions to this provision occur when a SCR's eligible Installed Capacity is set to zero throughout the period of the SCR Change of Status, when a SCR's eligible Installed Capacity is decreased by at least the same kW value as the reported SCR Change of Status, or if a SCR Change of Status is reported, and prior to the second performance test, the SCR returns to the full applicable ACL enrolled prior to the SCR Change of Status. Performance in both performance tests shall be used in calculation of the resource's performance factors and all associated

performance factors, deficiencies and penalties. If the RIP fails to report the performance for a resource that was required to perform in the second performance test in the Capability Period: (a) the resource will be assigned a performance of zero (0) for the test hour, and (b) the RIP shall be evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

#### **5.12.11.1.4 Average Coincident Load of an SCR Aggregation**

The ISO shall compute the Average Coincident Load of an SCR Aggregation each month in accordance with ISO Procedures.

#### **5.12.11.1.5 Use of an Incremental Average Coincident Load**

Beginning with the Summer 2014 Capability Period, a Responsible Interface Party may report any qualifying increase to a Special Case Resource's Average Coincident Load as Incremental Average Coincident Load in the RIP enrollment file upload and in accordance with this Services Tariff and ISO Procedures.

For SCRs with a total Load increase equal to or greater than twenty (20) percent and less than thirty (30) percent of the applicable ACL, the RIP may enroll the SCR with an Incremental ACL provided that the eligible Installed Capacity does not increase from the prior enrollment months within the same Capability Period and prior to enrollment with an Incremental ACL. If the SCR is enrolled with an Incremental ACL and it is the first month of the SCR's enrollment in the applicable Capability Period, the enrolled eligible Installed Capacity value shall not exceed the maximum eligible Installed Capacity of the SCR from the Prior Equivalent Capability Period. When no enrollment exists for the SCR in the Prior Equivalent Capability Period and it is the first month of the SCR's enrollment in the applicable Capability Period, the enrolled eligible Installed Capacity of the SCR shall not exceed the ACL calculated from the Capability Period SCR Load Zone Peak Hours. For SCRs with a total Load increase equal to or greater than thirty

(30) percent of the applicable ACL, the RIP may enroll the SCR with an Incremental ACL and an increase to the SCR's eligible Installed Capacity and is required to test as described in this section of the Service Tariff.

The ISO shall adjust the ACL of the SCR for an Incremental ACL for all months for which the Incremental ACL is reported by the RIP. For resources reporting an Incremental ACL, the Net ACL shall equal the enrolled ACL plus the reported Incremental ACL less any applicable SCR Change of Status and shall be the basis for the upper limit of ICAP for which the RIP may enroll the SCR during the Capability Period.

An Incremental ACL is a discrete change to the SCR operations that is expected to result in an increase to the Load that the SCR will consume from the NYS Transmission System and/or distribution system. It is not available to account for random fluctuations in Load, such as those caused by weather or other seasonal Load variations. Therefore, the ACL of a SCR may only be increased once per Capability Period and the amount of the increase enrolled must remain the same for all months for which the Incremental ACL is reported. A SCR enrolled in the Capability Period with an Incremental ACL may not be enrolled by another RIP for the remainder of the Capability Period. A SCR enrolled in the Capability Period with a Provisional ACL is not eligible to enroll with an Incremental ACL.

Following the Capability Period for which a SCR has been enrolled with an Incremental ACL, the RIP shall provide the hourly metered Load verification data that corresponds to the Monthly SCR Load Zone Peak Hours identified by the ISO for all months in which an Incremental ACL value was reported for the SCR. For each month for which verification data was required to be reported, the ISO shall calculate a Monthly ACL that will be used in the calculation of a Verified ACL. The Monthly ACL shall equal the average of the SCR's top

twenty (20) one-hour metered Load values that correspond with the applicable Monthly SCR Load Zone Peak Hours, and taking into account (i) the resource's reported verified Load reduction in a Transmission Owner's demand response program in hours coincident with any of these hours and (ii) the resource's verified Load reduction in either of the ISO's economic demand response programs (the Day Ahead Demand Response Program and the Demand Side Ancillary Services Program) in hours coincident with any of these hours. For the Day Ahead Demand Response Program, the verified Load reduction that occurred in response to a DADRP schedule shall be added to the Monthly SCR Load Zone Peak Hour for which the reduction in response to a DADRP schedule occurred. For the Demand Side Ancillary Services Program, the Load value to be used in calculating the Monthly ACL for each hour during the Monthly SCR Load Zone Peak Hours in which a non-zero Base Point Signal the ISO provides to the resource, shall be the greater of (a) the DSASP Baseline MW value in the interval immediately preceding the first non-zero Base Point Signal in the Monthly SCR Load Zone Peak Hour and (b) the metered Load of the resource as reported by the RIP for the Monthly SCR Load Zone Peak Hour. When the non-zero Base Point Signal dispatch of a DSASP resource begins in one hour and continues into consecutive hours, and the consecutive hour is identified as being a Monthly SCR Load Zone Peak Hour, the DSASP Baseline MW value in effect at the beginning of the dispatch of the non-zero Base Point Signal shall be the MW value used for purposes of determining the applicable Load value for that Monthly SCR Load Zone Peak Hour, in accordance with the preceding sentence. The Verified ACL shall be the average of the two (2) highest Monthly ACLs during the Capability Period in which the SCR was enrolled with an Incremental ACL within the same Capability Period.

For any month in which verification data for the Incremental ACL is required but not timely submitted to the ISO in accordance with ISO procedures, the ISO shall set the metered Load values to zero. When a Monthly ACL is set to zero, the Verified ACL will be calculated as the average of: a) the two (2) highest Monthly ACLs during the Capability Period in which the SCR was enrolled with an Incremental ACL within the same Capability Period; plus b) the Monthly ACLs for all months in which the SCR was enrolled within the same Capability Period with an Incremental ACL in the Capability Period in which the RIP failed to provide the minimum verification data required. In addition, a RIP may be subject to a penalty for each month for which verification data was required and not reported in accordance with this Services Tariff.

For each SCR that is enrolled with an Incremental ACL, the ISO shall compare the Net ACL calculated from the resource enrollment (ACL plus Incremental ACL less any applicable SCR Change of Status) to the Verified ACL calculated for the SCR to determine if the RIP's use of an Incremental ACL may have resulted in a shortfall pursuant to Section 5.14.2.

A Special Case Resource that was required to perform in the first performance test in the Capability Period in accordance with ISO Procedures and was subsequently enrolled using an Incremental ACL and an increase in the amount of Installed Capacity that the SCR is eligible to sell, shall be required to demonstrate performance against the maximum amount of eligible Installed Capacity reported for the SCR in the second performance test in the Capability Period. Performance in this test shall be measured from the Net ACL. Performance in both performance tests shall be used in calculation of the resource's performance factor and all associated performance factors, deficiencies and penalties. If the RIP fails to report the performance for a resource that was required to perform in the second performance test in the Capability Period: (a)

the resource will be assigned a performance of zero (0) for the test hour, and (b) the RIP shall be evaluated for failure to report under Section 5.12.12.2 of this Services Tariff.

#### **5.12.11.2 Existing Municipally-Owned Generation**

A municipal utility that owns existing generation in excess of its Unforced Capacity requirement, net of NYPA-provided Capacity may, consistent with the deliverability requirements set forth in Attachment X and Attachment S to the ISO OATT, offer the excess Capacity for sale as Installed Capacity provided that it is willing to operate the generation at the ISO's request, and provided that the Energy produced is deliverable to the New York State Power System. Such a municipal utility shall not be required to comply with the requirement of Section 5.12.7 of this Tariff that an Installed Capacity Supplier bid into the Energy market or enter into Bilateral Transactions. Municipal utilities shall, however, be required to submit their typical physical operating parameters, such as their start-up times, to the ISO. This subsection is only applicable to municipally-owned generation in service or under construction as of December 31, 1999.

#### **5.12.11.3 Energy Limited Resources**

An Energy Limited Resource may, consistent with the deliverability requirements set forth in Attachment X and Attachment S to the ISO OATT, qualify as an Installed Capacity Supplier if it Bids its Installed Capacity Equivalent into the Day-Ahead Market each day and if it is able to provide the Energy equivalent of the Unforced Capacity for at least four (4) consecutive hours each day. Energy Limited Resources shall also Bid a Normal Upper Operating Limit or Emergency Upper Operating Limit, as applicable, designating their desired operating limits. Energy Limited Resources that are not scheduled in the Day-Ahead Market to operate at a level above their bid-in upper operating limit, may be scheduled in the RTC, or may

be called in real-time pursuant to a manual intervention by ISO dispatchers, who will account for the fact that Energy Limited Resource may not be capable of responding.

#### **5.12.11.4 Intermittent Power Resources**

Intermittent Power Resources that depend upon wind or solar as their fuel may qualify as Installed Capacity Suppliers, without having to comply with the daily bidding and scheduling requirements set forth in Section 5.12.7 of this Tariff, and may, consistent with the deliverability requirements set forth in Attachment X and Attachment S to the ISO OATT, claim up to their nameplate Capacity as Installed Capacity. To qualify as Installed Capacity Suppliers, such Intermittent Power Resources shall comply with the requirements of Section 5.12.1 and the outage notification requirements of 5.12.7 of this Tariff.

#### **5.12.12 Sanctions Applicable to Installed Capacity Suppliers and Transmission Owners**

Pursuant to this section, the ISO may impose financial sanctions on Installed Capacity Suppliers and Transmission Owners that fail to comply with certain provisions of this Tariff. The ISO shall notify Installed Capacity Suppliers and Transmission Owners prior to imposing any sanction and shall afford them a reasonable opportunity to demonstrate that they should not be sanctioned and/or to offer mitigating reasons why they should be subject to a lesser sanction. The ISO may impose a sanction lower than the maximum amounts allowed by this section at its sole discretion. Installed Capacity Suppliers and Transmission Owners may challenge any sanction imposed by the ISO pursuant to the ISO Dispute Resolution Procedures.

Any sanctions collected by the ISO pursuant to this section will be applied to reduce the Rate Schedule 1 charge under this Tariff.

#### **5.12.12.1 Sanctions for Failing to Provide Required Information**

If (i) an Installed Capacity Supplier fails to provide the information required by Sections 5.12.1.1, 5.12.1.2, 5.12.1.3, 5.12.1.4, 5.12.1.7 or 5.12.1.8 of this Tariff in a timely fashion, or (ii) a Supplier of Unforced Capacity from External System Resources located in an External Control Area or from a Control Area System Resource that has agreed not to Curtail the Energy associated with such Installed Capacity, or to afford it the same Curtailment priority that it affords its own Control Area Load, fails to provide the information required for certification as an Installed Capacity Supplier established in the ISO Procedures, the ISO may take the following actions: On the first day that required information is late, the ISO shall notify the Installed Capacity Supplier that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of the following day. Starting on the third day that the required information is late, the ISO may impose a daily financial sanction of up to the higher of \$500 or \$5 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing. Starting on the tenth day that the required information is late, the ISO may impose a daily financial sanction of up to the higher of \$1000 or \$10 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing.

If an Installed Capacity Supplier fails to provide the information required by Subsection 5.12.1.5 of this Tariff in a timely fashion, the ISO may take the following actions: On the first calendar day that required information is late, the ISO shall notify the Installed Capacity Supplier that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of that first calendar day. Starting on the second calendar day that the required information is late, the ISO may impose a daily financial sanction

up to the higher of \$500 or \$5 per MW of Installed Capacity that the Generator, System Resource, or Control Area System Resource in question is capable of providing.

If a TO fails to provide the information required by Subsection 5.11.3 of this Tariff in a timely fashion, the ISO may take the following actions: On the first day that required information is late, the ISO shall notify the TO that required information is past due and that it reserves the right to impose financial sanctions if the information is not provided by the end of the following day. Starting on the third day that the required information is late, the ISO may impose a daily financial sanction up to \$5,000 a day. Starting on the tenth day that required information is late, the ISO may impose a daily financial sanction up to \$10,000.

#### **5.12.12.2 Sanctions for Failing to Comply with Scheduling, Bidding, and Notification Requirements**

On any day in which an Installed Capacity Supplier fails to comply with the scheduling, bidding, or notification requirements of Sections 5.12.1.6 or 5.12.1.10, or with Section 5.12.7 of this Tariff, or in which a Supplier of Installed Capacity from External System Resources or Control Area System Resources located in an External Control Area that has agreed not to Curtail the Energy associated with such Installed Capacity, or to afford it the same Curtailment priority that it affords its own Control Area Load, fails to comply with scheduling, bidding, or notification requirements for certification as an Installed Capacity Supplier established in the ISO Procedures, the ISO may impose a financial sanction up to the product of a deficiency charge (pro-rated on a daily basis) and the maximum number of MWs that the Installed Capacity Supplier failed to schedule or Bid in any hour in that day provided, however, that no financial sanction shall apply to any Installed Capacity Supplier who demonstrates that the Energy it schedules, bids, or declares to be unavailable on any day is not less than the Installed Capacity that it supplies for that day rounded down to the nearest 0.1 MW, or rounded down to the nearest

whole MW for an External Installed Capacity Supplier. The deficiency charge may be up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction corresponding to where the Installed Capacity Supplier's capacity cleared, and for each month in which the Installed Capacity Supplier is determined not to have complied with the foregoing requirements.

In addition, if any Installed Capacity Supplier fails to comply with the scheduling, bidding, or notification requirements of Sections 5.12.1.6 or 5.12.1.10, or with Section 5.12.7 of this Tariff, or if an Installed Capacity Supplier of Unforced Capacity from an External Control Area fails to comply with the scheduling, bidding, or notification requirements for certification as an Installed Capacity Supplier established in the ISO Procedures during an hour in which the ISO curtails Exports associated with NYCA Installed Capacity Suppliers consistent with Section 5.12.10 of this Tariff and with ISO Procedures, then the ISO may impose an additional financial sanction equal to the product of the number of MWs the Installed Capacity Supplier failed to schedule during that hour and the corresponding Real-Time LBMP at the applicable Proxy Generator Bus.

To the extent an Installed Capacity Supplier of Unforced Capacity from an External Control Area or an External Generator associated with an Unforced Capacity sale using UDRs or EDRs fails to comply with Section 5.12.1.10 of this Tariff, the Installed Capacity Supplier or External Generator associated with an Unforced Capacity sale using UDRs or EDRs shall be subject to a deficiency charge calculated in accordance with the formula set forth below for each Obligation Procurement Period:

$$Deficiency\ charge = 1.5 * PRICE * \left( \frac{1000kW}{1MW} \right) * \left( \frac{\sum_{n=1}^N (\max( ICAP_n^{MWh} - SRE_n^{MWh}, 0))}{N} \right)$$

Where:

$N$  = total number of hours of SRE calls during the relevant Obligation Procurement Period

$PRICE$  = ICAP Spot Market Auction clearing price for the relevant Obligation Procurement Period

$ICAP_n^{MWh}$  = for each hour  $n$  of SRE calls during the relevant Obligation Procurement Period, the ICAP equivalent of the UCAP sold from the External Installed Capacity Supplier that is a Generator, or the External Generator associated with an Unforced Capacity sale using UDRs or EDRs, or the Control Area System Resource in MWh, minus (x) any MWh that are unavailable due to an outage as defined in the ISO Procedures, or due to physical operating limitations affecting the External Installed Capacity Supplier that is a Generator, or the External Generator associated with an Unforced Capacity sale using UDRs or EDRs, or due to other operational issues that the ISO determines to be outside the Installed Capacity Supplier's control, and (y) any MWh that were Bid as Imports to the NYCA at the appropriate Proxy Generator Bus at a price that was designed to ensure the Import was scheduled to the greatest extent possible, but that were not scheduled by the ISO

$SRE_n^{MWh}$  = MWh provided to the NYCA at the appropriate Proxy Generator Bus from the External Installed Capacity Supplier that is a Generator, or the External Generator associated with an Unforced Capacity sale using UDRs or EDRs, or the Control Area System Resource, during each hour  $n$  of SRE calls during the relevant Obligation Procurement Period.

If an Installed Capacity Supplier's failure to fully comply with this Tariff would, in addition to being assessed a deficiency charge calculated in accordance with the formula set forth above, also permit the ISO to impose a different deficiency charge or a financial sanction under this Section 5.12.12.2, or to impose a deficiency charge for a shortfall under Section 5.14.2.2 of this Tariff, then the ISO shall only impose the penalty for failure to comply with Section 5.12.1.10 of this Tariff on the Installed Capacity Supplier for the hour(s) in which the Installed Capacity Supplier failed to meet its obligations under Section 5.12.1.10 of this Tariff.

If the Installed Capacity Supplier is a Responsible Interface Party that enrolled a SCR with an Incremental ACL in accordance with this Services Tariff, and also reported an increase to the Installed Capacity the SCR has eligible to sell after the first performance test in the Capability Period, the ISO may impose an additional financial sanction due to the failure of the RIP to report the required performance of the SCR against the Net ACL value in the second performance test in the Capability Period. This sanction shall be the value of the reported increase in the eligible Installed Capacity associated with the SCR that was sold by the RIP in each month of the Capability Period, during which the reported increase was in effect, multiplied by up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each such month.

If the Installed Capacity Supplier is a Responsible Interface Party, and the Average Coincident Load of the Special Case Resource has been decreased after the first performance test in the Capability Period, due to a SCR Change of Status in accordance with this Services Tariff and ISO Procedures, the ISO may impose an additional financial sanction resulting from the failure of the RIP to report the required performance of the SCR against the Net ACL value of the SCR when the SCR was required to perform in the second performance test in the Capability

Period in accordance with Section 5.12.11.1.3.2 of this Services Tariff. This sanction shall be the value of the Unforced Capacity equivalent of the SCR Change of Status MW reported for the SCR during the months for which the SCR was enrolled with a SCR Change of Status and was required to demonstrate in the second performance test as specified in Section 5.12.11.1.3.2 of this Services Tariff, multiplied by up to one and one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each such month.

If a RIP fails to provide the information required by Section 5.12.11.1.3 of this Services Tariff in accordance with the ISO Procedures for reporting a Qualified Change of Status Condition, and the ISO determines that a SCR Change of Status occurred within a Capability Period, the ISO may impose a financial sanction equal to the difference, if positive, between the enrolled ACL and the maximum one hour metered Load for the month multiplied by up to one-half times the applicable Market-Clearing Price of Unforced Capacity determined in the ICAP Spot Market Auction for each month the Installed Capacity Supplier is deemed to have a shortfall in addition to the corresponding shortfall penalty as provided in Section 5.14.2.

For each month in which a RIP fails to report required verification data and the applicable ACL value is set to zero in accordance with Section 5.12.11 of this Services Tariff, the ISO shall have the right to recover any energy payments made to the RIP for performance of the SCR by reducing other payments or other lawful means.

## **7.2 Billing and Payment Procedures**

For purposes of this Section 7.2:

- (i) the term “Complete Week Settlement Period” shall mean the seven day period between Saturday and Friday for which all of the days are in the same month; and
- (ii) the term “Stub Week Settlement Period” shall mean the six or fewer day period between Saturday and Friday for which all of the days are in the same month.

### **7.2.1 Billing and Settlement Information**

The ISO shall provide settlement and billing information to Customers. The ISO shall inform each Customer that provides or is provided services furnished under this ISO Services Tariff or the ISO OATT of the payments due for such service. Such information shall be made electronically available to the Customer.

### **7.2.2 Invoicing and Payment**

#### **7.2.2.1 Weekly Invoice**

On or about each Wednesday, as set forth in ISO Procedures, the ISO shall submit an invoice to a Customer that indicates the net amount owed by or owed to the Customer for those services furnished under this ISO Services Tariff or the ISO OATT for the previous Complete Week Settlement Period or Stub Week Settlement Period that are designated as Weekly Invoice Components in ISO Procedures; *provided, however*, that the net amount owed by or owed to the Customer for those services furnished for a Stub Week Settlement Period that concludes a month shall be included in the next monthly invoice issued in accordance with Section 7.2.2.2 of this ISO Services Tariff.

### **7.2.2.2 Monthly Invoice**

Within five (5) business days after the first day of each month, the ISO shall submit an invoice to a Customer that indicates the net amount owed by or owed to the Customer:

- (i) for those services furnished under this ISO Services Tariff or the ISO OATT for a Stub Week Settlement Period that concludes the previous month that are designated as Weekly Invoice Components in ISO Procedures;
- (ii) for any adjustments to amounts contained in the weekly invoices issued in the previous month pursuant to Section 7.2.2.1 of this ISO Services Tariff;
- (iii) for those services furnished under this ISO Services Tariff or the ISO OATT in the previous month that are designated as Monthly Invoice Components in ISO Procedures;
- (iv) for any adjustments to amounts contained in a previously issued monthly invoice that was issued on or about one hundred twenty (120) days prior to the issuance of this invoice;  
and
- (v) for any adjustments to amounts contained in a previously issued monthly invoice as part of the Close-Out Settlement of that monthly invoice pursuant to Section 7.4.1.2 of this ISO Services Tariff.

### **7.2.2.3 Payment by the Customer**

A Customer owing payments on net in its weekly invoice or its monthly invoice shall make those payments to the ISO through the ISO Clearing Account by the second business day after the date on which the weekly invoice or monthly invoice is rendered by the ISO unless otherwise specified in ISO Procedures. In accordance with Section 7.1.2 of this ISO Services

Tariff, the ISO may net any overpayment by the Customer for past estimated charges against current amounts due from the Customer or, if the Customer has no outstanding amounts due, the ISO may pay to the Customer an amount equal to the overpayment.

#### **7.2.2.4 Payment by the ISO**

Except as provided in Section 7.1.4 of this ISO Services Tariff, the ISO shall pay all net monies owed to a Customer in its weekly invoice or its monthly invoice from the ISO Clearing Account by the second business day after the due date for Customer payments set forth in Section 7.2.2.3 of this ISO Services Tariff unless otherwise specified in ISO Procedures.

#### **7.2.3 Use of Estimated Data and Meter Data**

The ISO may use estimates, including estimated meter data, in whole or in part to settle a weekly or monthly invoice in accordance with ISO Procedures. The ISO shall use meter data submitted to the ISO in accordance with Article 13 of this ISO Services Tariff. Any charges based on estimates shall be subject to true-up in invoices subsequently issued by the ISO after the ISO has obtained the requisite actual information, provided that the ISO shall only true-up charges based on meter data prior to the deadline for finalizing meter data established in Section 7.4 of this ISO Services Tariff. A trued-up charge shall include interest amounts calculated at the rate set forth in Section 7.3 of this ISO Services Tariff from the weekly or monthly due date for the charge until the date of payment of the trued-up amount for that charge.

#### **7.2.4 Method of Payment**

All payments by the Customer shall be made by either (i) wire transfer in immediately available funds payable to the ISO through the ISO Clearing Account or (ii) any other method set forth in ISO Procedures. All payments by the ISO shall be made either (i) by wire transfer in

immediately available funds payable to the Customer by the ISO through the ISO Clearing Account or (ii) any other method set forth in ISO Procedures.

### **7.2.5 TCC Auction Settlements**

Notwithstanding Sections 7.2.2.1 and 7.2.2.2 of this ISO Services Tariff, the ISO shall make settlements related to the Centralized TCC Auction and the Reconfiguration Auction as set forth in this Section 7.2.5.

7.2.5.1 The ISO shall submit invoices to, and make settlements with, Transmission Owners in connection with the allocation of Net Auction Revenues in accordance with the timeline set forth in ISO Procedures.

7.2.5.2 Customers owing payments to the ISO as a result of their activity in or related to a Centralized TCC Auction or Reconfiguration Auction, pursuant to an award notice or a comparable invoice rendered by the ISO, shall make those payments to the ISO through the ISO Clearing Account in accordance with the timeline set forth in ISO Procedures.

7.2.5.3 Except as provided in Section 7.1.4 of this ISO Service Tariff, the ISO shall pay all net monies owed to Customers as a result of their activity in or related to a Centralized TCC Auction or a Reconfiguration Auction, pursuant to an award notice or a comparable invoice rendered by the ISO, from the ISO Clearing Account in accordance with ISO Procedures.

7.2.5.4 Sections 7.2.1, 7.2.3, 7.2.4, and 7.2.6 of this ISO Services Tariff and Section 19.9.6 of Attachment M of the ISO OATT shall apply to settlements calculated in accordance with this Section 7.2.5.

## **7.2.6 Verification of Payments**

The ISO shall verify that all payments owed by Customers in accordance with this ISO Services Tariff and the ISO OATT have been paid to the ISO in a timely manner. If a Customer fails to make a payment within the time period established in Sections 7.2.2.1, 7.2.2.2, and 7.2.5 of this ISO Services Tariff or pays less than the amount due, the ISO shall take measures pursuant to Section 7.5 of this ISO Services Tariff. Except as provided in Section 7.1.4 of this ISO Services Tariff, the ISO shall also ensure that monies owed to Customers in accordance with this ISO Services Tariff and the ISO OATT are paid through the ISO Clearing Account in a timely manner.

## **7.2.7 Payments for TSCs**

Bills and payments for TSCs shall be issued in accordance with the ISO OATT. Accordingly, this Section 7 shall not apply to TSCs.

## **7.2.8 Payment for Actual Energy Withdrawals by Energy Storage Resources**

A Customer that is participating in the ISO-administered Energy and Ancillary Services markets with an Energy Storage Resource will be subject to Day Ahead Market settlements pursuant to Section 4.2.6 and Real Time Market settlements pursuant to 4.5.2, or in the case of a Supplier of Regulation Service pursuant to Rate Schedule 15.3.6.1 of this ISO Services Tariff. If a Load Serving Entity requires the Energy Storage Resource to also pay a retail rate for its charging withdrawals, then the ISO shall issue a credit to the affected Customer for the associated Actual Energy Withdrawals and assess a charge to this Load Serving Entity for the same Actual Energy Withdrawals. The credit and offsetting charge shall be calculated as the product of the Actual Energy Withdrawals of the Energy Storage Resource and the time

weighted average Real-Time Market LBMP for the hour at the Energy Storage Resource's location.

## **13 Metering**

### **13.1 General Requirements**

Existing metering in the NYCA provides revenue-quality metering information among the currently designated electrical zones separated by the designated transmission Interfaces. In addition, sufficient metering information will be made available by the ISO to calculate Load for the individual Transmission Owners within each Load Zone. The ISO will require adequate metering for all Generators and Loads within the NYCA to ensure the reliable operation of the NYS Power System.

### **13.2 Requirements Pertaining to Customers**

Customers shall provide to the ISO such information and data as the ISO reasonably deems necessary in order to perform its functions and fulfill its responsibilities under the ISO Services Tariff and in accordance with the ISO Market Power Monitoring Program. Such information will be provided on a timely basis and in the formats prescribed in the ISO Procedures. The ISO shall establish metering specifications and standards for all metering that is used as a data source by the ISO. Customers shall install and maintain such metering at their own expense, and deliver data to the ISO without charge.

A Customer taking service under the ISO Services Tariff will make available to the ISO metered data that meets ISO requirements by one of the following means: (i) direct transmission to the ISO; (ii) direct transmission to the ISO through Transmission Owner communications equipment, or (iii) indirectly through metering provided by the Transmission Owner in whose Load Zone it is located.

The Customer also shall provide its metered data to the Transmission Owner in whose Load Zone it is located, to the extent that the Transmission Owner determines that the metered data provided to the ISO is required for its system operation and planning functions, for the billing of services it provides to the Customer, or to perform calculations required as part of the ISO Settlement procedures.

### **13.2.1 Load Serving Entities**

Any Load that is not directly metered, as described above, will have its Load determined by the Transmission Owner in whose Load Zone it is located in accordance with the Transmission Owner's retail access plan on file with the PSC or otherwise authorized.

### **13.2.2 Ancillary Service Suppliers**

Suppliers shall ensure that adequate metering data is made available to the ISO as described above. Additionally, for operational purposes, metered data provided to the ISO must also simultaneously be provided to the Transmission Owner, which will handle such information in conformity with the OASIS standards of conduct as specified in Order No. 889.

### **13.2.3 Estimation of Metering**

In the event of a meter malfunction or inadequate metering data, the ISO may use estimates to determine Customer's rights and responsibilities under the ISO Services Tariff.

### **13.2.4 Energy Storage Resources**

In addition to the metering requirements applicable to Energy Storage Resources because they are Generators, specific metering rules apply to account for Energy injections and withdrawals.

13.2.4.1 An Energy Storage Resource, including an Energy Storage Resource that is electrically located behind the same point of interconnection as a load facility or other Resource, must separately and directly meter Energy injections and withdrawals of the Energy Storage Resource. Such metering must allow the Meter Authority and/or ISO is able to distinguish the Energy injections and withdrawals of the Energy Storage Resource from all other injections and withdrawals behind the point of interconnection.

13.2.4.2 Hourly meter data for Energy Storage Resources shall be reported as two separate components: (i) Energy injections, and (ii) Energy withdrawals. Each component shall be submitted to the NYISO by the Meter Authority in separate fields such that the ISO is able to separately determine the total Energy injections and withdrawals in each interval.

13.2.4.3 If an Energy Storage Resource is electrically located behind the same point of interconnection as a load facility, the Meter Authority shall submit to the ISO (i) directly metered Energy injection and withdrawal data (pursuant to Services Tariff § 13.2.4.2), and (ii) the Load (excluding the Energy injections and withdrawals of the Energy Storage Resource) of the co-located facility behind the point of interconnection (pursuant to OATT § 2.7.4.2.1 (ii) & (iv)).

The ISO Procedures, including the Revenue Meter Requirements Manual (M-25), Control Center Requirements Manual (M-21), and Accounting and Billing Manual (M-14) contain additional information related to metering requirements for Generators and Energy Storage Resources.

### **13.3 Metering Requirements for Demand Side Resources**

#### **13.3.1 Responsibility for Metering and Meter Data Services for Aggregations and Demand Side Resources**

##### **13.3.1.1 An Aggregator, Responsible Interface Party, or Curtailment Service**

Provider shall obtain metering and meter data services, as these services are defined in ISO Procedures, from: (i) the Member System in which Transmission District the Aggregation or Demand Side Resource is located, and/or (ii) an authorized Meter Services Entity that the ISO has determined complies with the eligibility requirements pursuant to Section 13.3.2.1. A Responsible Interface Party, or Curtailment Service Provider that meets the eligibility requirements in Section 13.3.2.1 may serve as its own Meter Services Entity.

13.3.1.2 The Responsible Interface Party or Curtailment Service Provider shall be responsible for ensuring that all of the metering and meter data services that are required for it to perform its functions and fulfill its responsibilities under the ISO Tariffs and ISO Procedures are provided by the Member System and/or Meter Services Entity in accordance with the requirements in this Section 13 and ISO Procedures. The Responsible Interface Party or Curtailment Service Provider shall be responsible for any applicable penalties issued as a result of metering or meter data services that do not comply with the ISO Tariffs and ISO Procedures, including, but not limited to, penalties issued pursuant to Services Tariff Sections 5.12 and 5.14.

13.3.1.3 A Responsible Interface Party or Curtailment Service Provider shall be responsible for any required compensation to the Member System and/or Meter Services Entity concerning the provision of metering and/or meter data services.

In accordance with Services Tariff Section 15.10 (Rate Schedule 10), Responsible Interface Parties and Curtailment Service Providers shall be responsible for the ISO's costs of conducting audits pursuant to Section 13.3.2.3.

### **13.3.2 Meter Services Entity Requirements**

#### **13.3.2.1 Eligibility Determination for Meter Services Entity**

To be authorized as a Meter Services Entity, an entity must complete, to the NYISO's satisfaction, the application requirements specified in Services Tariff Section 13.3.2.1.2 below. Once authorized, a Meter Services Entity must meet the obligations set forth in Services Tariff Sections 13.3.2.1.3 and 13.3.2.1.4. All physical metering infrastructure and meter data communications infrastructure used by a Meter Services Entity must comply with the requirements set forth in the ISO Tariffs and ISO Procedures.

13.3.2.1.1 An entity, including a Responsible Interface Party or Curtailment Service Provider, seeking to be a Meter Services Entity must submit to the ISO an application containing the eligibility information required pursuant to Section 13.3.2.1.2, accompanied by a non-refundable application fee of \$1,000. The ISO shall review the application within thirty (30) calendar days of its receipt of the application and fee, and notify the applicant whether the application is sufficient to register the applicant as a Meter Services Entity or otherwise requires additional information. Any additional information required shall be received by the ISO within the timeframe specified by the ISO in its request for additional information. The ISO shall reject the application of an entity seeking to become a Meter Services Entity if the required information is not received within the specified timeframe or an alternative, mutually agreed to timeframe.

Upon the ISO's affirmative determination of an entity's eligibility, the entity will be registered with the ISO and authorized to serve as a Meter Services Entity in order to provide metering and/or meter data services, as applicable, to a Responsible Interface Party or Curtailment Service Provider. The ISO shall post on its website a list of all authorized Meter Services Entities.

If the ISO determines an entity is not eligible to serve as a Meter Services Entity, the ISO shall provide the entity with the reasons for such determination. An entity that seeks to re-apply to be a Meter Services Entity shall also be required to pay the \$1,000 application fee.

13.3.2.1.2 An entity seeking to be a Meter Services Entity must provide, at a minimum, the following eligibility information, as detailed in ISO Procedures: (i) financial eligibility and insurance coverage information; (ii) proof of eligibility to do business in New York State; (iii) a list of the Transmission Owner(s) service territory(ies) in which it will provide services; (iv) a description of the metering and/or meter data services that it will provide; (v) its attestation of its employees' qualifications, training, and certification to perform the listed services; (vi) a description of the meter testing laboratory facilities, including its attestation that its meter testing programs comply with ISO Procedures and Good Utility Practice; (vii) its agreement that its services will be subject to audit by the ISO, the Transmission Owners, and/or their designated agents, as applicable; (viii) its agreement to comply with the metering requirements in the ISO Tariffs and ISO Procedures, as such requirements may be amended from time to time; (ix) a revenue-grade settlement meter and real-time telemetry data plan; (x) a meter data validation, editing, and estimation plan; (xi) a security plan and description of

how it will protect meter equipment and/or meter data from unauthorized physical or electronic entry or tampering; (xii) a description of how and where records of meter installations and/or meter data will be kept, and its agreement to retain these records in accordance with the ISO's recordkeeping requirements; and (xiii) any other information required by ISO Procedures or requested by the ISO.

13.3.2.1.3 A Meter Services Entity shall promptly inform the ISO, in accordance with ISO procedures, of any material change to the eligibility information it has previously submitted to the ISO pursuant to Section 13.3.2.1.2. The ISO shall review all such material changes and determine whether the Meter Services Entity complies with all eligibility requirements. If the NYISO determines that the Meter Services Entity does not comply with the eligibility requirements, it may suspend the Meter Services Entity's eligibility until such time that it complies with those eligibility requirements.

13.3.2.1.4 The ISO shall inform registered Meter Services Entities of changes related to Meter Services Entity eligibility requirements via posting to the ISO's public website and electronic mail. A Meter Services Entity has a continuing obligation to comply with the eligibility requirements in this Section 13 and ISO Procedures and the metering and meter data requirements in the ISO Tariffs and ISO Procedures, as the requirements may be amended from time to time. Each Meter Services Entity shall inform the ISO, in accordance with ISO Procedures, and received by the date specified in the ISO's posting, of its compliance with the identified changes to eligibility criteria. If the Meter Services Entity is unable to comply with the changes by the specified date, it shall provide the ISO with a

detailed plan to comply. The ISO shall review all such plans and determine whether to extend the compliance deadline, or to suspend the Meter Services Entity's eligibility until such time that it complies with all eligibility requirements.

### **13.3.2.2 Standards of Conduct for Meter Services Entities**

A Meter Services Entity must treat all customers, Affiliated and non-Affiliated, on a non-discriminatory basis, and must not make or grant any undue preference or advantage to any person or subject any person to any undue prejudice or disadvantage with respect to the provision of metering services authorized by Services Tariff Section 13.3.

### **13.3.2.3 ISO Audits and Corrective Actions**

13.3.2.3.1 The ISO or its designated entity may, upon reasonable notice, perform an audit, inspection, and/or test of the Meter Services Entity's metering facilities, meters, and/or meter data records to ensure they comply with the ISO Tariffs and ISO Procedures and with the Meter Services Entity's plans submitted to the ISO. Meter Services Entities must comply with, i) periodic audits of meter data records and meter data collection and retention services and protocols provided to the Market Participant by the Meter Services Entity; and ii) audits of the metering facilities, meter data records and meter data collection and retention services and protocols utilized by the Market Participant and the Meter Services Entity when the Market Participant enrolls new resources or modifies the metering scheme of existing resources.

The ISO's audit of a MSE's services may involve, but is not limited to, the ISO's review, inspection, performance testing and review of corrective actions taken in the following categories:

- A) Validation, Estimation, & Editing (VEE) methodology;
- B) Site meter configurations;
- C) Meter compliance with ISO rules and procedures;
- D) Meter Services Entity operational protocols, procedures, and record keeping, and compliance with ISO rules and procedures; and
- E) Telemetry and communication data and records.

13.3.2.3.2 If the ISO determines, at any time, that a Meter Services Entity does not comply with the eligibility requirements or does not comply with the metering or meter data requirements set forth in the ISO Tariffs and ISO Procedures, the ISO may suspend or revoke the eligibility of the Meter Services Entity.