

# Attachment VI

## 2.3 Definitions - C

**Capability Period:** Six-month periods which are established as follows: (i) from May 1 through October 31 of each year (“Summer Capability Period”); and (ii) from November 1 of each year through April 30 of the following year (“Winter Capability Period”).

**Capability Period Auction:** An auction conducted no later than thirty (30) days prior to the start of each Capability Period in which Unforced Capacity may be purchased and sold in a six-month strip.

**Capability Period SCR Load Zone Peak Hours:** The top forty (40) coincident peak hours that, prior to the Summer 2014 Capability Period include hour beginning thirteen through hour beginning eighteen and beginning with the Summer 2014 Capability Period include hour beginning eleven through hour beginning nineteen. The Capability Period SCR Load Zone Peak Hours shall be determined by the NYISO from the Prior Equivalent Capability Period and shall be used by RIPs to report ACL values for the purpose of SCR enrollment. For a SCR enrolled with a Provisional ACL that requires verification data to be reported at the end of the Capability Period in which the SCR was enrolled, the Capability Period SCR Load Zone Peak Hours shall be determined from the Capability Period in which the SCR was enrolled. Such hours shall not include (i) hours in which Special Case Resources located in the specific Load Zone were called by the ISO to respond to a reliability event or test and (ii) hours for which the Emergency Demand Response Program resources were deployed by the ISO in each specific Load Zone. In addition, beginning with the Summer 2014 Capability Period, the NYISO shall not include, in descending rank order of NYCA Load up to a maximum of eight hours per Capability Period, a) the hour before the start time of a reliability event or performance test, in which SCRs located in the specific Load Zone were called by the ISO to respond to a reliability event or performance test, or b) the hour immediately following the end time of such reliability event or performance test.

**Capability Year:** A Summer Capability Period, followed by a Winter Capability Period (*i.e.*, May 1 through April 30).

**Capacity:** The capability to generate or transmit electrical power, or the ability to control demand at the direction of the ISO, measured in megawatts (“MW”).

**Capacity Accreditation Factor:** Subject to Section 5.11.7 of this ISO Services Tariff, the factors, set annually by the ISO in accordance with Section 5.12.14.3 and ISO Procedures, that reflect the marginal reliability contribution of the ICAP Suppliers within each Capacity Accreditation Resource Class toward meeting NYSRC resource adequacy requirements for the upcoming Capability Year. Capacity Accreditation Factors for each Capacity Accreditation Resource Class will be determined by the ISO for Rest of State, G-J Locality (excluding Load Zone J), NYC Locality, and Long Island Locality, in accordance with Section 5.12.14.3 and ISO Procedures. Capacity Accreditation Factors are applicable to all Resources and/or Aggregations within each Capacity Accreditation Resource Class that has been established in accordance with ISO Procedures.

**Capacity Accreditation Resource Class:** A defined set of Resources and/or Aggregations, as identified in accordance with ISO Procedures, with similar technologies and/or operating characteristics which are expected to have similar marginal reliability contributions toward meeting NYSRC resource adequacy requirements for the upcoming Capability Year. Subject to Section 5.11.7 of this ISO Services Tariff, each Capacity Accreditation Resource Class will be evaluated through the annual review detailed in Section 5.12.14.3. Each Installed Capacity Supplier will be assigned a Capacity Accreditation Resource Class.

**Capacity Limited Resource:** Prior to May 1, 2025, a Resource that is constrained in its ability to supply Energy above its Normal Upper Operating Limit by operational or plant configuration characteristics became a Capacity Limited Resource by registering its Capacity limiting characteristics with, and justify them to, the ISO consistent with ISO Procedures. Prior to May 1, 2025, Capacity Limited Resources may submit a schedule indicating that their Normal Upper Operating Limit is a function depending on one or more variables, such as temperature or pondage levels, in which case the Normal Upper Operating Limit applicable at any time shall be determined by reference to that schedule. After April 30, 2025, Resources shall no longer be able to able to participate as Capacity Limited Resources in the Installed Capacity Market.

**Capacity Reservation Cap:** As defined in the ISO OATT.

**CARL Data:** Control Area Resource and Load (“CARL”) data submitted by Control Area System Resources to the ISO.

**Centralized Transmission Congestion Contracts (“TCC”) Auction (“Auction”):** As defined in the ISO OATT.

**Champlain Hudson Power Express Merchant Transmission Facility (“CHPE MTF”):** A transmission facility that interconnects the NYCA at Astoria Annex in Queens, New York to the Hydro-Québec Control Area at Hertel, La Prairie, Québec.

**Co-located Storage Resources (“CSR”):** An Energy Storage Resource and one other type of Generator that is not a Withdrawal-Eligible Generator. The second participating Generator can be a wind, solar, or landfill gas fueled Intermittent Power Resource, a Limited Control Run-of-River Hydro Resource, or a Dispatchable Generator which may require commitment and time to start-up. The two Generators must: (a) both be located behind a single Point of Injection (as defined in Section 1.16 of the OATT); (b) participate in the ISO Administered Markets as two distinct Generators; and (c) share a set of CSR Scheduling Limits. Generators that may not participate in the ISO-Administered Markets as components of a CSR include: (a) Limited Energy Storage Resources, (b) a Generator comprised of a group of generating units at a single location, which grouped generating units are separately committed and dispatched by the ISO, and for which Energy injections are measured at a single location, (c) Generators participating via a model that can accommodate several participants, including but not limited to Hybrid Storage Resources and Aggregations, and (d) Generators that serve a Host Load.

**Code of Conduct:** The rules, procedures and restrictions concerning the conduct of the ISO directors and employees, contained in Attachment F to the ISO Open Access Transmission Tariff.

**Commenced Repair:** A determination by the ISO that a Market Participant with a Generator i) has decided to pursue the repair of its Generator, and based on the ISO's technical/engineering evaluation ii) has a Repair Plan for the Generator that is consistent with a Credible Repair Plan, and iii) has made appropriate progress in pursuing the repair of its Generator when measured against the milestones of a Credible Repair Plan.

**Commission ("FERC"):** The Federal Energy Regulatory Commission, or any successor agency.

**Compensable Overgeneration:** A quantity of Energy provided over a given RTD interval in which a Supplier has offered Energy that exceeds the Real-Time Scheduled Energy established by the ISO for that Supplier and for which the Supplier may be paid pursuant to ISO Procedures.

For (i) Suppliers not covered by other provisions of this Section, (ii) Intermittent Power Resources depending on wind or solar energy as their fuel for which the ISO has imposed a Wind and Solar Output Limit in the given RTD interval, and (iii) Intermittent Power Resources depending on landfill gas as their fuel or Limited Control Run-of-River Hydroelectric Resources that participate as Co-located Storage Resources for which the ISO has imposed a Wind and Solar Output Limit in the given RTD interval, Compensable Overgeneration shall initially equal three percent ( 3%) of the Supplier's Normal Upper Operating Limit which may be modified by the ISO if necessary to maintain good Control Performance.

For a Generator or Aggregation: (i) which is operating in Start-Up or Shutdown Periods, or Testing Periods; or (ii) which is a Limited Control Run of River Hydro Resource that has offered its Energy to the ISO in a given interval not using the ISO-committed Flexible or Self-Committed Flexible bid mode (except as provided above); or (iii) which is an Intermittent Power Resource that depends on landfill gas for its fuel and has offered its Energy to the ISO in a given interval not using the ISO-committed Flexible or Self-Committed Flexible bid mode (except as provided above); or (iv) which is an Intermittent Power Resource that depends on wind or solar energy for its fuel (except as provided above), Compensable Overgeneration shall mean all Energy actually injected by the Generator or Aggregation that exceeds the Real-Time Scheduled Energy established by the ISO for that Generator or Aggregation.

For a Generator or Aggregation operating in intervals when it has been designated as operating Out of Merit at the request of a Transmission Owner or the ISO, Compensable Overgeneration shall mean all Energy actually provided by the Generator or Aggregation that exceeds the Real-Time Scheduled Energy up to the Energy level directed by the Transmission Owner or the ISO.

For a Generator comprised of a group of generating units at a single location, which grouped generating units are separately committed and dispatched by the ISO, and for which Energy injections are measured at a single location, Compensable Overgeneration shall mean that quantity of Energy injected by the Generator, during the period when one of its grouped generating units is operating in a Start-Up or Shutdown Period, that exceeds the Real-Time Scheduled Energy established by the ISO for that period, for that Generator, and for which the Generator may be paid pursuant to ISO Procedures.

**Completed Application:** An Application that satisfies all of the information and other requirements for service under the ISO Services Tariff.

**Confidential Information:** Information and/or data that has been designated by a Customer to be proprietary and confidential, provided that such designation is consistent with the ISO Procedures, the ISO Services Tariff, and the ISO Code of Conduct.

**Congestion:** A characteristic of the transmission system produced by a constraint on the optimum economic operation of the power system, such that the marginal price of Energy to serve the next increment of Load, exclusive of losses, at different locations on the transmission system is unequal.

**Congestion Component:** The component of the LBMP measured at a location or the Transmission Usage Charge between two locations that is attributable to the cost of transmission Congestion as is more completely defined in Attachment B of the Services Tariff.

**Congestion Rent:** As defined in the ISO OATT.

**Congestion Rent Shortfall:** As defined in the ISO OATT.

**Constraint:** An upper or lower limit placed on a variable or set of variables that are used by the ISO in its SCUC, RTC, or RTD programs to control and/or facilitate the operation of the NYS Transmission System.

**Contingency:** An actual or potential unexpected failure or outage of a system component, such as a Generator, transmission line, circuit breaker, switch or other electrical element. A Contingency also may include multiple components, which are related by situations leading to simultaneous component outages.

**Control Area:** An electric system or combination of electric power systems to which a common Automatic Generation Control scheme is applied in order to: (1) match, at all times, the power output of the Generators and Aggregations within the electric power system(s) and Capacity and Energy purchased from entities outside the electric power system(s), with the Load within the electric power system(s); (2) maintain scheduled interchange with other Control Areas, within the limits of Good Utility Practice; (3) maintain the frequency of the electric power system(s) within reasonable limits in accordance with Good Utility Practice; and (4) provide sufficient Capacity to maintain Operating Reserves in accordance with Good Utility Practice.

**Control Area System Resource:** A set of Resources owned or controlled by an entity within a Control Area that also is the operator of such Control Area. Entities supplying Unforced Capacity using Control Area System Resources will not designate particular Resources as the suppliers of Unforced Capacity.

**Control Performance:** A standard for measuring the degree to which a Control Area is providing Regulation Service in conformance with NERC requirements.

**Controllable Transmission:** Any Transmission facility over which power-flow can be directly controlled by power-flow control devices without having to re-dispatch generation.

**Credible Repair Plan:** A Repair Plan that meets the requirements described in Section 5.18.1.4 of this Services Tariff and in ISO Procedures.

**Credit Assessment:** An assessment of a Customer's creditworthiness, conducted by the ISO in accordance with Section 26.5.3 of Attachment K to this Services Tariff.

**Critical Electric System Infrastructure Load:** Load that is critical to maintaining the reliable operation of electric system infrastructure, including, without limitation, Load that is (i) necessary to maintain the delivery of natural gas, fuel oil, and other fuels used by Generators (including Local Generators) to generate electricity, (ii) likely to impact the supply of natural gas, fuel oil, and other fuel to Generators, or (iii) otherwise likely to impact Generator operation. Critical Electric System Infrastructure Load does not include on-site Load that is consumed for ancillary purposes unless such Load is necessary for compliance with parts (i) – (iii) of this definition.

**Cross-Sound Scheduled Line:** A transmission facility that interconnects the NYCA to the New England Control Area at Shoreham, New York and terminates near New Haven, Connecticut.

**CSR Scheduling Limits:** The CSR injection Scheduling Limit is used to determine the combined Regulation Capacity, Operating Reserve and Energy injection schedules for, and the maximum permitted net injection by a CSR's Generators. The CSR withdrawal Scheduling Limit sets is used to determine the combined Regulation Capacity and Energy withdrawal schedules for, and the maximum permitted net withdrawal by a CSR's Generators.

The Market Participant that is responsible for submitting Bids for a set of CSR Generators shall submit a CSR injection Scheduling Limit and a CSR withdrawal Scheduling Limit with the hourly Day-Ahead and Real-Time Market Bids it submits for each of the CSR Generators. The CSR Scheduling Limit values that the Market Participant submits must reflect the physical capability to inject or withdraw Energy at the Point of Injection/Point of Withdrawal.

To address the real-time variability of Energy deliveries from the Intermittent Power Resource or Limited Control Run-of-River Hydro Resource that participate as Co-located Storage Resources, when the participating Energy Storage Resource has a non-zero Regulation and/or Operating Reserves schedule or is dispatched to inject Energy, and the sum of the participating Energy Storage Resource's and the participating Intermittent Power Resource's or Limited Control Run-of-River Hydro Resource's Energy, Regulation Service and Operating Reserves Schedules is greater than or equal to a specified percentage of the CSR injection Scheduling Limit, then the ISO will issue a Wind and Solar Output Limit to the Intermittent Power Resource or Limited Control Run-of-River Hydro Resource to not exceed its Base Point Signal. The specified percentage that is ordinarily used will be posted on the ISO's website.

**CTS Enabled Interface:** An External Interface at which the ISO has authorized the use of Coordinated Transaction Scheduling ("CTS") market rules and which includes a CTS Enabled Proxy Generator Bus for New York and a CTS Enabled Proxy Generator Bus for the neighboring Control Area.

**CTS Enabled Proxy Generator Bus:** A Proxy Generator Bus at which the ISO either requires or permits the use of CTS Interface Bids for Import and Export Transactions in the Real-Time

Market and requires the use of Decremental Bids for Wheels Through in the Real-Time Market. A CTS Enabled Proxy Generator Bus at which the ISO permits CTS Interface Bids will also permit Decremental and Sink Price Cap Bids.

**CTS Interface Bid:** A Real-Time Bid provided by an entity engaged in an External Transaction at a CTS Enabled Interface. CTS Interface Bids shall include a MW amount, a direction indicating whether the proposed Transaction is to Import Energy to, or Export Energy from, the New York Control Area, and a Bid Price.

**CTS Sink:** Representation of the location(s) within a Control Area where energy associated with a CTS Interface Bid is withdrawn. The NYCA CTS Sinks are Proxy Generator Buses.

**CTS Sink Price:** The price at a CTS Sink.

**CTS Source:** Representation of the location(s) within a Control Area where energy associated with a CTS Interface Bid is injected. The NYCA CTS Sources are Proxy Generator Buses.

**CTS Source Price:** The price at a CTS Source.

**Curtailement or Curtail:** A reduction in Transmission Service in response to a transmission Capacity shortage as a result of system reliability conditions.

**Curtailement Services Provider:** A qualified entity that can produce real-time, verified reductions in NYCA Load of at least 100 kW in a single Load Zone, pursuant to the Emergency Demand Response Program and related ISO procedures. The procedure for qualifying as a Curtailement Services Provider is set forth in Section 3 below and in ISO Procedures.

**Curtailement Services Provider Capacity:** Capacity from a Demand Side Resource nominated by a Curtailement Services Provider for participation in the Emergency Demand Response Program.

**Customer:** An entity which has complied with the requirements contained in the ISO Services Tariff, including having signed a Service Agreement, and is qualified to utilize the Market Services and the Control Area Services provided by the ISO under the ISO Services Tariff; provided, however, that a party taking services under the Tariff pursuant to an unsigned Service Agreement filed with the Commission by the ISO shall be deemed a Customer.

## 2.13 Definitions - M

**Major Emergency State:** An Emergency accompanied by abnormal frequency, abnormal voltage and/or equipment overloads that create a serious risk that the reliability of the NYS Power System could be adversely affected.

**Marginal Losses:** The NYS Transmission System Real Power Losses associated with each additional MWh of consumption by Load, or each additional MWh transmitted under a Bilateral Transaction as measured at the Points of Withdrawal.

**Marginal Losses Component:** The component of LBMP at a bus that accounts for the Marginal Losses, as measured between that bus and the Reference Bus.

**Market-Clearing Price:** The price determined in an Installed Capacity auction for each ISO-defined Locality, the remainder of the NYCA and each adjacent External Control Area for which all offers to sell and bids to purchase Unforced Capacity are in equilibrium.

**Market Mitigation and Analysis Department:** A department, internal to the ISO, that is responsible for participating in the ISO's administration of its Tariffs. The Market Mitigation and Analysis Department's duties are described in Section 30.3 of the Market Monitoring Plan that is set forth in Attachment O to this Services Tariff.

**Market Monitoring Unit:** "Market Monitoring Unit" shall have the same meaning in this ISO Services Tariff as it has in the Market Monitoring Plan that is set forth in Attachment O to this Services Tariff.

**Market Participant:** An entity, excluding the ISO, that produces, transmits, sells, and/or purchase for resale Unforced Capacity, Energy or Ancillary Services in the Wholesale Market. Market Participants include: Transmission Customers under the ISO OATT, Customers under the ISO Services Tariff, Power Exchanges, Transmission Owners, Primary Holders, LSEs, Suppliers and their designated agents. Market Participants also include entities buying or selling TCCs.

**Market Problem:** An issue which requires notification to Market Participants, the Commission and the Market Monitoring Unit pursuant to Section 3.5.1 of this Services Tariff. It includes market design flaws, software implementation and modeling anomalies or errors, market data anomalies or errors, and economic inefficiencies that have a material effect on the ISO-administered markets or transmission service. The term does not include erroneous Energy or Ancillary Services prices (which are managed through procedures outlined in Attachment E to the Services Tariff) or erroneous customer settlements.

**Market Services:** Services provided by the ISO under the ISO Services Tariff related to the ISO Administered Markets for Energy, Capacity and Ancillary Services.

**MCZ Import Constrained Locality:** A Mitigated Capacity Zone that is also an Import Constrained Locality.

**Member Systems:** The eight Transmission Owners that comprised the membership of the New York Power Pool, which are: (1) Central Hudson Gas & Electric Corporation, (2) Consolidated Edison Company of New York, Inc., (3) New York State Electric & Gas Corporation, (4) Niagara Mohawk Power Corporation d/b/a National Grid, (5) Orange and Rockland Utilities, Inc., (6) Rochester Gas and Electric Corporation, (7) the Power Authority of the State of New York, and (8) Long Island Lighting Company d/b/a Long Island Power Authority.

**Meter Services Entity (“MSE”):** An entity registered with the ISO and authorized to provide metering and meter data services, as applicable, to an Aggregator, Responsible Interface Party, or Curtailment Service Provider.

**Minimum Generation Bid:** A two-parameter Bid that identifies the minimum operating level a Supplier requires to operate a Generator, and the payment a Supplier requires to operate its Generator at that level. If the Supplier is a BTM:NG Resource, LESR, Energy Storage Resource, or an Aggregation, it shall not submit a Minimum Generation Bid.

**Minimum Generation Level:** For purposes of describing the eligibility of ten minute Resources to be committed by the Real Time Dispatch for pricing purposes pursuant to the Services Tariff, Section 4.4.3.3, an upper bound, established by the ISO, on the physical minimum generation limits specified by ten minute Resources. Ten minute Resources with physical minimum generation limits that exceed this upper bound will not be committed by the Real Time Dispatch for pricing purposes. The ISO shall establish a Minimum Generation Level based on its evaluation of the extent to which it is meeting its reliability criteria including Control Performance. The Minimum Generation Level, in megawatts, and the ISO's rationale for that level, shall be made available through the ISO's website or comparable means. If the Supplier is a BTM:NG Resource, LESR, Energy Storage Resource, or Aggregation, it shall not submit a Minimum Generation Level.

**Minimum Payment Nomination:** An offer, submitted by a Responsible Interface Party, in dollars per Megawatt-hour and not to exceed \$500 per Megawatt-hour, to reduce Load equal to the Installed Capacity Equivalent of the amount of Unforced Capacity a Special Case Resource is supplying to the NYCA.

**Mitigated Capacity Zone:** New York City and any Locality added to the definition of “Locality” accepted by the Commission on or after March 31, 2013.

**Modified Wheeling Agreement (“MWA”):** A Transmission Wheeling Agreement between Transmission Owners that was in existence at the time of ISO start-up, as amended and modified as described in Attachment K. Modified Wheeling Agreements are associated with Generators or power supply contracts existing at ISO start-up. All Modified Wheeling Agreements are listed in Attachment L, Table 1A, and are designated in the “Treatment” column of Table 1A, as “MWA”.

**Monthly Auction:** An auction administered by the ISO pursuant to Section 5.13.3 of the ISO Services Tariff.

**Monthly Average Coincident Load (“Monthly ACL”):** Beginning with the Summer 2014 Capability Period, the Load value calculated for each month during a Capability Period

applicable to a Special Case Resource with a reported Incremental Average Coincident Load. The Monthly ACL is an average of the SCR's metered hourly Load that is supplied by the NYS Transmission System and/or the distribution system and reported for the Monthly SCR Load Zone Peak Hours applicable to such SCR. The calculation and verification data reporting requirements are provided in Section 5.12.11.1.5 of this Services Tariff and ISO Procedures. Any Load supported by generation produced from a Local Generator, other behind-the-meter generator, or other supply source located behind the meter operating during the Monthly SCR Zone Load Peak Hours may not be included in the metered Load values reported for the Monthly ACL.

**Monthly Net Benefit Threshold:** The price, in \$/MWh, determined by the ISO pursuant to Section 4.5.7.1 of the ISO Services Tariff and ISO Procedures.

**Monthly SCR Load Zone Peak Hours:** Beginning with the Summer 2014 Capability Period, the top forty (40) coincident peak hours for each month within a Capability Period that include hour beginning eleven through hour beginning nineteen as identified by the ISO for each Load Zone; provided, however, that such hours shall not include (i) hours in which Special Case Resources located in the specific Load Zone were called by the ISO to respond to a reliability event or test, (ii) hours for which the Emergency Demand Response Program resources were deployed by the ISO in each specific Load Zone and (iii) in descending rank order of NYCA Load up to a maximum of eight hours per month, a) the hour before the start time of a reliability event or performance test, in which SCRs located in the specific Load Zone were called by the ISO to respond to a reliability event or performance test, or b) the hour immediately following the end time of such reliability event or performance test.

**Mothball Outage:** The outage state in which a Market Participant's Generator is voluntarily removed from service on or after May 1, 2015, with applicable prior notice, for reasons not related to equipment failure. A Generator in Mothball Outage is subject to the return-to-service provisions in Section 5.18.4 of this Services Tariff and is ineligible to participate in the Installed Capacity market.

**MTF Reservation:** A right to submit a Bid into the NYISO Day-Ahead and/or Real-Time Markets over the Champlain Hudson Power Express MTF that is obtained in accordance with the rules and procedures established pursuant to Attachment II to the ISO OATT. *See* ISO OATT Sections 41.1.8 and 41.3.1.

## 2.17 Definitions - Q

**Qualified Change of Load Condition:** A Special Case Resource enrolled with an Average Coincident Load, Provisional Average Coincident Load, or Net Average Coincident Load, in accordance with this Services Tariff, meets a Qualified Change of Load Condition when: (i) the SCR is expected to have a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than seven (7) consecutive days, (ii) the SCR is experiencing a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than seven (7) consecutive days, or (iii) the SCR experienced an unanticipated reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold for a period greater than seven (7) consecutive days within any month in which the SCR sold capacity or adjoining months in which the SCR sold capacity in either month.

**Qualified Change of Status Condition:** A Special Case Resource enrolled with an Average Coincident Load, Provisional Average Coincident Load, or Net Average Coincident Load, in accordance with this Services Tariff meets a Qualified Change of Status Condition when: (i) the SCR is expected to have a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that will extend for a period of greater than sixty (60) consecutive days, (ii) the SCR is experiencing a reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that is expected to continue for a total period that is greater than sixty (60) consecutive days, or (iii) the SCR has experienced an unanticipated reduction in total Load that meets or exceeds the SCR Load Change Reporting Threshold that has existed for a period greater than sixty (60) consecutive days in which the SCR sold capacity.

**Qualified Non-Generator Voltage Support Resource:** A resource that is neither a Generator, nor a Distributed Energy Resource, nor a synchronous condenser but that is capable of providing the ISO with Reactive Power on a dynamic basis, that is energized and under the operational control of the ISO, or a Transmission Owner, that meets the resource-specific technical and testing criteria specified in the ISO Procedures, and that is ineligible to receive Reactive Power compensation other than as a Qualified Non-Generator Voltage Support Resource. The Cross-Sound Scheduled Line and the Champlain Hudson Power Express MTF shall be Qualified Non-Generator Voltage Support Resources, provided that they meet the technical and testing criteria in the ISO Procedures.

**Quick Start Mode:** The setting of a block of generator units capable of remote start-up by a Transmission Owner so that it can synchronize and reach full output within fifteen (15) minutes.

**Quick Start Reserves:** Capacity of a block of generator units that is set to Quick Start Mode by request of a Transmission Owner.

## 2.18 Definitions - R

**Ramp Capacity:** The amount of change in the Desired Net Interchange that generation located in the NYCA can support at any given time. Ramp capacity may be calculated for all Interfaces between the NYCA and neighboring Control Areas as a whole or for any individual Interface between the NYCA and an adjoining Control Area.

**RCRR TCC:** As defined in the ISO OATT.

**Reactive Power (MVar):** The product of voltage and the out-of-phase component of alternating current. Reactive Power, usually measured in MVar, is produced by capacitors (synchronous condensers), Qualified Non-Generator Voltage Support Resources, and over-excited Generators and absorbed by reactors or under-excited Generators and other inductive devices including the inductive portion of Loads.

**Real Power Losses:** The loss of Energy, resulting from transporting power over the NYS Transmission System, between the Point of Injection and Point of Withdrawal of that Energy.

**Real-Time Bid:** A Bid submitted into the Real-Time Commitment before the close of the Real-Time Scheduling Window. A Real-Time Bid shall also include a CTS Interface Bid.

**Real-Time Commitment (“RTC”):** A multi-period security constrained unit commitment and dispatch model that co-optimizes to solve simultaneously for Load, Operating Reserves and Regulation Service on a least as-bid production cost basis over a two hour and fifteen minute optimization period. The optimization evaluates the next ten points in time separated by fifteen minute intervals. Each RTC run within an hour shall have a designation indicating the time at which its results are posted; “RTC<sub>00</sub>,” “RTC<sub>15</sub>,” “RTC<sub>30</sub>,” and “RTC<sub>45</sub>” post on the hour, and at fifteen, thirty, and forty-five minutes after the hour, respectively. Each RTC run will produce binding commitment instructions for the periods beginning fifteen and thirty minutes after its scheduled posting time and will produce advisory commitment guidance for the remainder of the optimization period. RTC<sub>15</sub> will also establish hourly External Transaction schedules, while all RTC runs may establish 15 minute External Transaction schedules at Variably Scheduled Proxy Generator Buses. Additional information about RTC’s functions is provided in Section 4.4.2 of this ISO Services Tariff.

**Real-Time Dispatch (“RTD”):** A multi-period security constrained dispatch model that co-optimizes to solve simultaneously for Load, Operating Reserves, and Regulation Service on a least-as-bid production cost basis over a fifty, fifty-five or sixty-minute period (depending on when each RTD run occurs within an hour). The Real-Time Dispatch dispatches, but does not commit, Resources, except that RTD may commit, for pricing purposes, Resources meeting Minimum Generation Levels and capable of starting in ten minutes. RTD may also establish 5 minute External Transaction schedules at Dynamically Scheduled Proxy Generator Buses. Real-Time Dispatch runs will normally occur every five minutes. Additional information about RTD’s functions is provided in Section 4.4.3 of this ISO Services Tariff. Throughout this ISO Services Tariff the term “RTD” will normally be used to refer to both the Real-Time Dispatch and to the specialized Real-Time Dispatch Corrective Action Mode software.

**Real-Time Dispatch–Corrective Action Mode (“RTD-CAM”):** A specialized version of the Real-Time Dispatch software that will be activated when it is needed to address unanticipated system conditions. RTD-CAM is described in Section 4.4.4 of this ISO Services Tariff.

**Real-Time LBMP:** The LBMPs established through the ISO Administered Real-Time Market.

**Real-Time Market:** The ISO Administered Markets for Energy and Ancillary Services resulting from the operation of the RTC and RTD.

**Real-Time Minimum Run Qualified Gas Turbine:** One or more gas turbines, offered in the Real-Time Market, which, because of their physical operating characteristics, may qualify for a minimum run time of two hours in the Real-Time Market. Characteristics that qualify gas turbines for this treatment are established by ISO Procedures and include using waste heat from the gas turbine-generated electricity to make steam for the generation of additional electricity via a steam turbine.

**Real-Time Scheduled Energy:** The quantity of Energy that a Supplier is directed to provide in real-time by the ISO. Injections and Demand Reductions are indicated by positive Base Point Signals and withdrawals are indicated by negative Base Point Signals. Unless otherwise directed by the ISO, Dispatchable Supplier’s Real-Time Scheduled Energy is equal to its RTD Base Point Signal, or, if it is providing Regulation Service, to its AGC Base Point Signal, and an ISO-Committed Fixed or Self-Committed Fixed Supplier’s Real-Time Scheduled Energy is equal to its bid output level in real-time.

**Real-Time Scheduling Window:** The period of time within which the ISO accepts offers and bids to sell and purchase Energy and Ancillary Services in the Real-Time Market for a given hour which period closes seventy-five (75) minutes before the start of that hour, or eighty-five (85) minutes before the start of that hour for Bids to schedule External Transactions at the Proxy Generator Buses associated with the Cross-Sound Scheduled Line, the Neptune Scheduled Line, the Linden VFT Scheduled Line, the HTP Scheduled Line, or the Champlain Hudson Power Express MTF.

**Reconfiguration Auction:** As defined in the ISO OATT.

**Reference Bus:** The location on the NYS Transmission System relative to which all mathematical quantities, including Shift Factors and penalty factors relating to physical operation, will be calculated. The NYPA Marcy 345 kV transmission substation is designated as the Reference Bus.

**Reference Month:** For purposes of the Net Benefits Test, the calendar month that is twelve months prior to the Study Month.

**Regulation Capacity:** The Energy capability, measured in MW, that a Regulation Service provider offers and/or which it is scheduled to provide for Regulation Service.

**Regulation Capacity Market Price:** The price for Regulation Capacity determined by the ISO pursuant to section 15.3 of this Services Tariff.

**Regulation Capacity Response Rate:** The Regulation Capacity a Resource is capable of providing over five minutes, measured in MW/minute which shall not exceed the lowest normal energy response rate provided for the Resource and which must be sufficient to permit that Resource to provide the Regulation Capacity (in MW) offered within a five-minute RTD interval. Reference to a Regulation response rate shall be a reference to the Regulation Capacity Response Rate.

**Regulation Movement:** The absolute value of the change in Energy over a six second interval, measured in MW, that a Regulation Service provider is instructed to deliver for the purpose of providing Regulation Service.

**Regulation Movement Market Price:** The price for Regulation Movement as determined by the ISO pursuant to section 15.3 of this Services Tariff.

**Regulation Movement Multiplier:** A factor, used with the Regulation Movement Bids, to schedule Regulation Service providers in both the Day-Ahead and Real-Time Markets. The ISO calculates the Regulation Movement Multiplier, pursuant to ISO Procedures, based on the historical relationship between the number of MW of Regulation Capacity that the ISO seeks to maintain in each hour and the number of Regulation Movement MW instructed by AGC in each hour.

**Regulation Movement Response Rate:** The amount of Regulation Movement a Regulation Service provider is capable of delivering in six seconds which shall not be less than, but can be equal to or greater than, the Regulation Capacity Response Rate equivalent.

**Regulation Service:** The Ancillary Service defined by the Commission as “frequency regulation” and that is instructed as Regulation Capacity in the Day-Ahead Market and as Regulation Capacity and Regulation Movement in the Real-Time Market as is further described in Section 15.3 of the Services Tariff. Day-Ahead and Real-Time Bids to provide Regulation Service shall include a Bid for Regulation Capacity and a Bid for Regulation Movement. The Regulation Service requirement or target level shall be for MW of Regulation Capacity.

**Regulation Service Demand Curve:** A series of quantity/price points that defines the maximum Shadow Price for Regulation Service corresponding to each possible quantity of Resources that the ISO’s software may schedule to satisfy the ISO’s Regulation Service constraint. A single Regulation Service Demand Curve will apply to both the Day-Ahead Market and the Real-Time Market for Regulation Service. The Shadow Price for Regulation Service shall be used to calculate Regulation Service payments under Rate Schedule 3 of this ISO Services Tariff.

**Regulation Revenue Adjustment Charge (“RRAC”):** A charge that will be assessed against certain Regulation Service Providers that are providing Regulation Service under Section 15.3.6 of Rate Schedule 3 to this ISO Services Tariff.

**Regulation Revenue Adjustment Payment (“RRAP”):** A payment that will be made to certain Regulation Service Providers that are providing Regulation Service under Section 15.3.6 of Rate Schedule 3 to this ISO Services Tariff.

**Reliability Rules:** Those rules, standards, procedures and protocols developed and promulgated by the NYSRC, including Local Reliability Rules, in accordance with NERC, NPCC, FERC, PSC and NRC standards, rules and regulations and other criteria and pursuant to the NYSRC Agreement.

**Repair Plan:** A work plan, set of actions, and time frame for such actions, that is necessary to repair a Generator and return it to service as described in Section 5.18.1 of this Services Tariff.

**Required System Capability:** Generation capability required to meet an LSE's peak Load plus Installed Capacity Reserve obligation as defined in the Reliability Rules.

**Residual Adjustment:** The adjustment made to ISO costs that are recovered through Schedule 1 of the OATT. The Residual Adjustment is calculated pursuant to Schedule 1 of the OATT.

**Residual Capacity Reservation Right ("RCRR"):** As defined in the ISO OATT.

**Residual Transmission Capacity:** As defined in the ISO OATT.

**Resource:** An Aggregation, or an Energy Limited Resource, Energy Storage Resource, Limited Energy Storage Resource, Generator, Installed Capacity Marketer, Special Case Resource, Intermittent Power Resource, Limited Control Run of River Hydro Resource, municipally-owned generation, System Resource, BTM:NG Resource, Demand Side Resource or Control Area System Resource that is not participating in an Aggregation.

**Resource with Energy Duration Limitation:** A Resource that is not capable of supplying its ICAP equivalent of UCAP sold in each hour of the day due to a run-time limitation, such as an Energy storage limitation or permit restriction, and has elected an Energy Duration Limitation as specified in Section 5.12.14 of the ISO Services Tariff.

**Responsible Interface Party ("RIP"):** A Customer that is authorized by the ISO to be the Installed Capacity Supplier for one or more Special Case Resources and that agrees to certain notification and other requirements as set forth in this Services Tariff and in the ISO Procedures.

**Rest of State:** The set of all non-Locality NYCA LBMP Load Zones. As of the 2014/2015 Capability Year, Rest of State includes all NYCA LBMP Load Zones other than LBMP Load Zones G, H, I, J and K.

**Retired:** A Generator that has permanently ceased operating on or after May 1, 2015 either: i) pursuant to applicable notice; or ii) as a result of the expiration of its Mothball Outage or of its ICAP Ineligible Forced Outage.

**RMR Agreement:** Shall have the meaning specified in Section 1.18 of the ISO's Open Access Transmission Tariff.

**RMR Avoidable Costs:** Shall have the meaning specified in Section 1.18 of the ISO's Open Access Transmission Tariff.

**RMR Generator:** Shall have the meaning specified in Section 1.18 of the ISO's Open Access Transmission Tariff.

**Rolling RTC:** The RTC run that is used to schedule a given 15-minute External Transaction. The Rolling RTC may be an RTC00, RTC15, RTC30 or RTC45 run.

**Roundtrip Efficiency:** The ratio of energy injections to energy withdrawals for an Energy Storage Resource or Aggregation comprised entirely of Energy Storage Resources.